

 **EDVAX** DOOR ENTRY

MANUAL ENGLISH

**DUE FILI PLUS VIDEO AND
AUDIO DOOR ENTRY SYSTEMS** **VIEW**
IoT smart life

This document presents the functions, the main components and the general rules for sizing and building video door entry and door entry systems with the Elvox Due Fili Plus system. Please consult the General Catalogue for further devices. The technical information provided is not exhaustive of all the information required to build the systems: it is in any case necessary and indispensable to refer to the instructions that accompany each product.



Due Fili Plus technology, quick and flexible.



Due Fili Plus technology is used to create high-performing video entryphone and entryphone communication systems in all types of building, whether new builds or refurbishments, in the simplest possible way. Due Fili Plus technology guarantees faultless connections between all devices used for receiving and transmitting power, audio/video and data signals.



Up to 6400 indoor stations.

With Due Fili Plus technology, systems are designed to handle up to a maximum of **484 outdoor stations** and up to **6400 indoor stations**. With the **expansion interface**, you can expand the system by replicating several Due Fili Plus systems with **up to 32 blocks** and **128 reception video-switchboards**.

Up to 1200 metres.

Due Fili Plus technology can be used to create extended systems, with a distance between the indoor station and outdoor station of up to **1200 metres, without losing any audio or video signal quality**. The signal is carried along a single, small-diameter twisted-pair cable.

Simple configuration.

Due Fili Plus technology ensures really simple programming. The installer can programme the outdoor station directly from the indoor station. Once the indoor station has been encoded, the system can even simulate an audio/video call from the outdoor station, to check whether installation was successful straight away.

Remote management by smartphone and tablet.

The **View** App enables remote video door entry system management via smartphone and tablet in combination with the **Tab 7S Up** and **Tab 5S Up** video indoor stations. It allows you to receive a video entryphone call, see the video surveillance cameras or open your door wherever you are. What's more, it allows you to manage up to **10 mobile devices** and up to **5 different systems**.



Professionalism guaranteed.

Our professional, technologically sophisticated products are designed to guarantee superior performance and durability.

Solutions for any building.

Our video door entry system solutions adapt to the most diverse application environments. Versatility and scalability, combined with sophisticated technology and ease of use, are all distinguishing features which make them suitable for the smallest apartment to large shopping centres and executive compounds, through to large residences.

Index

Due Fili Plus video and audio door entry systems

| | |
|------------------------------------|-----|
| Video door entry functions | 6 |
| Outdoor stations | |
| - Functionality and modular design | |
| - Technical characteristics | |
| Indoor stations | 12 |
| - Functionality | |
| - Technical characteristics | |
| System components | 42 |
| - Technical characteristics | |
| Obsolete products | 56 |
| System | |
| - Technical characteristics | |
| - Absorption tables | |
| - Logical system sizing | |
| Multi-row diagrams | 126 |

Call from an outdoor station.

When a call is made from the outdoor station, the indoor station being called rings (entryphone) and displays (video entryphone) images recorded by the camera at the outdoor station.




To answer, lift the handset (for the handset version) or press the talk/listen button (for the hands-free version); to end the call, replace the handset or press the talk/listen button again.

Sending the call to a mobile device.


Video entryphones with integrated Wi-Fi, combined with the **Video Door** App, make it possible to receive a call, to view the video surveillance cameras, to open the door to your home, to activate auxiliary services (stair lighting, turning on the sprinkler system, etc.) directly from your smartphone or tablet, wherever you may be, indoors or out and about.

**Call from an outdoor station with several parallel outdoor stations.**

If the system contains **more than one outdoor station**, during the call sending phases or during a call between an entrance panel and an entryphone/video entryphone, the other outdoor stations will signal that the system is engaged in another conversation.

**Call from an outdoor station towards a group of indoor stations.**


When a call is made from the **outdoor station** towards a **group of indoor stations** (apartment/office), they ring simultaneously and display (video entryphone) the images recorded by the camera of the outdoor station (for the maximum number of video indoor stations simultaneously on, please refer to the consumption table). This function depends on the indoor station model used, please refer to the individual reference instruction manual.



The first indoor station that answers by lifting the handset or pressing the talk/listen button will begin communicating with the outdoor station, while the others will stop ringing and generate the engaged tone.

Confidential conversation.

During a call between the outdoor station and the indoor station, the confidentiality of the conversation is guaranteed. All the other objects not involved in the communication are excluded.




Intercom call.

The dedicated indoor stations programmed specifically for this purpose allow you to send an audio intercom call to another indoor station. If the indoor station called answers, the conversation begins. In this case too, the confidential conversation function guarantees its confidentiality. A possible call from an outdoor station or from a reception switchboard takes priority and interrupts the intercom call.


**Call to the reception switchboard.**

The two typical ways to make calls to the **switchboard**, once the function is active, are:

- for **hands-free indoor stations**, on standby press the "talk/listen" button (please refer to the model installed);
- for **indoor stations with a handset**, on standby press the "door lock" button.


**Landing call.**

This function is used to make a call to indoor stations, connecting a call button directly to the dedicated terminals of the indoor station itself. You can also set a ringtone or a different call tone from the outdoor station's.


**Self-start.**

With the system on standby, press the self-start button to turn on the camera on the outdoor station and the footage recorded will be shown on the display (only if it is a video entryphone).


If several outdoor stations and/or cameras are present, you can view the images from these, by pressing the self-start button repeatedly. The viewing order is automatically determined by the system (by default only the master entrance panel is intended for self-start). The section of the system can only be engaged by one communication at a time.

**Lock control.**

The **lock** button on all indoor stations operates the locks in the system. During a communication, if you press this button, you will release the lock connected to the calling outdoor station.




A second lock could be operated from a secondary outdoor station. In this case too, the lock will be released by pressing the **lock** button on the indoor station, during the call or during a conversation with that outdoor station, or following the self-start from the indoor station.




Professional firm function.

The dedicated indoor stations programmed specifically for this purpose, after a call from the outdoor station, automatically send the lock release control. This function is used mostly in doctor's surgeries, dental surgeries and offices in general. Some indoor stations make it possible to set the automatic activation of this function, also according to the days of the week and time brackets.


**Lock release with code from outdoor station.**

The door lock release control can also be enabled with numerical codes, fingerprints or RFID badges using the dedicated, duly programmed functional modules (please refer to the model installed).


**Actuation control with auxiliary outputs F1 and F2.**

From the indoor station, you can control timed actuations during a call or a conversation, using auxiliary functions F1 and F2. Using preliminary programming, you need to associate one of the push buttons on the indoor station with function F1 or F2.

The outdoor stations of series 1300, Steely and Patavium are equipped with outputs for auxiliary functions F1 and F2.

**Actuation control.**

From the indoor station, you can also control a timed actuation both with the system on standby and during a call or a conversation. The dedicated indoor stations have a push button dedicated to actuations; it is dedicated, as standard, to the activation of the first output of the first relay module.



OUTDOOR STATIONS.

Communicating is simple, effective and safe.

Outdoor stations are available in various dimensions and can be mounted in various ways, from surface mounting to flush mounting, monobloc, modular or special flush with the wall, but they all have one thing in common: an elegant and sophisticated design in keeping with the most demanding architectural requirements.

- **Pixel and Pixel Heavy** - just 10 cm wide, it can easily be installed in small spaces without compromising on either design or technological quality. In audio/video or audio only versions, Pixel and Pixel Heavy entrance panels are characterised by their **extensive modularity** which provides complete customisation of installation, combining different types of push buttons and a **3.5" colour LCD display**.



- **Pixel Up** - entrance panel with front cover plate made of 316 stainless steel with brushed finish, distinguished by a linear design and by a **reduced protrusion from the wall, of just 3 mm**. With **alphanumeric keyboard**, with stainless steel buttons and **colour display** with polycarbonate protective glass, with IP54 degree of protection and IK08 impact resistance.

- **1300 Series** - with soft and modern silhouettes and a scratch-resistant finish, suitable for any domestic context, in electro-polished anodised aluminium.

- **Steely** - boasting a design that is trendy, linear and simple. It is the perfect solution for innovative environments complementing a comprehensive range of stylistic requirements, building types and functional needs. Steely **by name**, steel by nature. A simple, hard-wearing material that characterises the DNA of the entrance panel and complements its contemporary, modern and technological style.



- **Patavium** - sinuous curves, beauty and sophistication, **ideal for refined environments as it** adapts to suit all types of architectures, particularly **historical buildings**. In **brass with an elegant satin finish**, also available on request in a **polished version** to enhance and endow every space with its very own personal form of expression.



Summary table of outdoor station functionality

| Type | Modular | | | | | |
|---|---|---|---|---|--|--|
| | Pixel | | Pixel Heavy | | | |
| Series |  |  |  |  | | |
| Call type | Push buttons | Alphanumeric with electronic contacts list | Push buttons | Alphanumeric with electronic contacts list | | |
| Audio version | ✓ | | ✓ | | | |
| Audio/video version | ✓ | | ✓ | | | |
| Installation | Flush mounting | ✓ | | ✓ | | |
| | Surface mounting | ✓ | | - | | |
| Material | Anodised aluminium | | Die-cast aluminium and Zamak | | | |
| Finishes | Grey Slate grey White Anodised grey | | Sable grey | | | |
| Maximum number of calls with keyboard | - | 6,400 ⁽¹⁾ | - | 6,400 ⁽¹⁾ | | |
| Maximum number of calls with push buttons | 42 (buttons along 1 row) | - | 42 (buttons along 1 row) | - | | |
| | 84 (buttons along 2 rows) | | 84 (buttons along 2 rows) | | | |
| Breadth of recording range HxV | 104°x83° | | 104°x83° | | | |
| Mechanical camera adjustment | - | | - | | | |
| Automatic audio microphone control (indoor and outdoor) | ✓ | | ✓ | | | |
| Echo cancellation ⁽²⁾ | ✓ | | ✓ | | | |
| call status LED indication | ✓ | | ✓ | | | |
| Indication: "BUSY-WAIT" | ✓ | ✓ | ✓ | ✓ | | |
| Name plate LED lighting colour | ✓ | ✓ | ✓ | ✓ | | |
| Teleloop for hearing aids | ✓ | | ✓ | | | |
| State voice synthesis | ✓ | | ✓ | | | |
| Door release with keyboard code | ✓ | | ✓ | | | |
| Door release with badge | ✓ | | ✓ | | | |
| Rain guard | ✓ | | - | | | |
| IP protection degree | IP54 | | IP54 | | | |
| IK Degree of resistance | IK08 | | IK10 | | | |

⁽¹⁾ The maximum number of calls is equivalent to the maximum number of indoor stations, divided up by a maximum of 200 indoor stations for each block and a maximum of 32 blocks per system (6,400 = 200 indoor stations x 32 blocks).

⁽²⁾ The echo cancellation algorithm means you can have natural, two-way conversations, automatically avoiding annoying audio feedback or whistling (Larsen effect), without having to adjust the microphone and speaker during installation.


| Flat | | | | Monobloc | | | |
|---|---|---|---|---|---|--|--------------------|
| Pixel Up | Patavium | Stelly | 1300 | 13K1 | 1300/E | | |
|  |  |  |  |  |  | | |
| Alphanumeric with electronic contacts list | Push buttons | Alphanumeric with electronic contacts list | Push buttons | Alphanumeric with electronic contacts list | Push buttons | Alphanumeric with electronic contacts list | Push buttons |
| ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| ✓ | - | - | - | ✓ | ✓ | ✓ | ✓ |
| 316 steel | Brass | | 316L steel | | Anodised aluminium | | Anodised aluminium |
| Brushed steel | Polished satin finish | | Brushed steel | | Electro-polished | | Electro-polished |
| 6,400 ⁽¹⁾ | - | 6,400 ⁽¹⁾ | - | 6,400 ⁽¹⁾ | - | 6,400 ⁽¹⁾ | - |
| - | 44 | - | 44 | - | 200 | 8 | 2 |
| 104°x83° | 84°x69° | | 84°x69° | | 84°x69° | | 100°x82° |
| - | - | | - | | - | | ✓ |
| ✓ | - | | - | | - | | - |
| ✓ | - | | - | | - | | - |
| ✓ | - | | - | | - | | - |
| ✓ | - | ✓ | - | ✓ | ✓ | ✓ | - |
| ✓ | - | ✓ | - | ✓ | ✓ | ✓ | - |
| ✓ | - | | - | | - | | - |
| ✓ | - | ✓ | - | ✓ | - | ✓ | - |
| ✓ | - | | - | | - | | - |
| ✓ | - | | - | | - | | - |
| IP54 | IP54 | | IP54 | | IP54 | | IP54 |
| IK08 | IK08 | IK07 | IK08 | IK07 | IK07 | IK07 | IK08 |

Pixel Series

Entrance panel installation

1-module entrance panel with push buttons

| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|



Up to 1

Up to 2

Up to 4

Up to 3


Up to 7

Up to 14

Up to 5


Up to 12

Up to 24



2-module entrance panel with push buttons



| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|



Up to 3

Up to 7

Up to 14



Up to 11

Up to 27


Up to 54

Pixel Series

Entrance panel installation

3-module entrance panel with push buttons


| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|



Up to 5

Up to 12


Up to 24



Up to 11

Up to 27


Up to 54



Up to 17

Up to 42


Up to 84



Key to Pixel buttons



Height of installation and recording range of entrance panels



Universal adaptors



If you are unable to change the box already mounted, use the Pixel 1- and 2-module universal adaptors (41135... or 41136...), which are compatible with the most commonly used flush mounting boxes on the market. The adaptors are compatible with the following distances between centres (min. - max):

- 1 module (192 - 197 mm);
- 2 modules (282.5 - 288.5 mm).

Pixel Heavy Series

Entrance panel installation



1-module entrance panel with push buttons

| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|




Up to 2

Up to 4



Up to 7

Up to 14




Up to 12

Up to 24



2-module entrance panel with push buttons

| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|




Up to 7

Up to 14



Up to 17

Up to 34



Up to 27


Up to 54

Pixel Heavy Series

Entrance panel installation

3-module entrance panel with push buttons

| Composition | Number of possible calls | Flush or surface mounting installation |
|-------------|--------------------------|--|
|-------------|--------------------------|--|




Up to 12

Up to 24




Up to 27

Up to 54



Up to 42

Up to 84



Key to Pixel Heavy buttons



Button on single row



Buttons on double row


Universal adaptors



If you are unable to change the box already mounted, use the Pixel 1- and 2-module universal adaptors (41135.02 or 41136.02), which are compatible with the most commonly used flush mounting boxes on the market. The adaptors are compatible with the following distances between centres (min. - max):

- 1 module (192 - 197 mm);
- 2 modules (282.5 - 288.5 mm).

Height of installation and recording range of entrance panels



Pixel and Pixel Heavy series.

Pixel and Pixel Heavy series entrance panel composition table


| Composition | Number of calls | Electronic units | | | | Electronic expansion units | | | | | | Installation | | | | Boxes and accessories | | | | | | | | | |
|-------------|-----------------|---|---|---|-------------------------|---|---|------------------------|-------------------------|---|---|-----------------------------|-------------------------|----------------------------|-------------------------|----------------------------|--------------------------------|--------------------------|----------------|-----------------------------|---|------------------------------------|---|---|--|
| | | Audio | | Audio/video | | Push buttons | | | | Name plates | LCD display | Alphanumeric keyboard | Access control keyboard | Digital fingerprint reader | Transponder reader | Blank front ⁽⁴⁾ | Mounting frame and cover plate | Boxes and accessories | | | | | | | |
| | | 41000 ⁽¹⁾ Basic | 41002 With teleloop and camera input | 41005 With teleloop and wide-angle camera | | 41010 10 buttons in a double row | | | | 41015 Name plates/ address number | 41018 | 41019 | 41020 | 41016 | 41017 | | | Flush mounting | Mounting boxes | Rain-proof frame (optional) | Surface mounting | | | | |
| | | Pixel front modules | | | | | | | | Pixel front modules | | | | | | | | Pixel installation | | | | | | | |
| Pixel | | 41100.yy ⁽³⁾ | | 41102.yy ⁽³⁾ | | 41105.yy ⁽³⁾ | | | | | | | | | | | | | | | | | | | |
| | | Buttons and blank module | | | | Buttons and blank module | | | | Buttons and blank module | | | | | | | | | | | | | | | |
| | | 41110 x 1 Single axial | 41110 x 2 Single axial | 41112 x 1 Double axial | 41111 x 2 Single rocker | 41110 x 1 Single axial | 41110 x 2 Single axial | 41112 x 1 Double axial | 41111 x 2 Single rocker | 41110 (max 5) Single axial | 41112 (max 2) Double axial | 41111 (max 5) Single rocker | | | | | | | | | | | | | |
| | | 41114.yy ⁽³⁾ Double blank module | 41113.yy ⁽³⁾ Single blank module | | | 41114.yy ⁽³⁾ Double blank module | 41113.yy ⁽³⁾ Single blank module | | | 41113.yy ⁽³⁾ (max 5) Single blank module | 41114.yy ⁽³⁾ (max 2) Double blank module | | | 41115 | 41118.yy ⁽³⁾ | 41119.yy ⁽³⁾ | 41119.yy ⁽³⁾ | 41116.yy ⁽³⁾ | 41117 | 41121.yy ⁽³⁾ | 41131.xx ⁽³⁾ 1 module Dim. 99.5x161 mm | 9191 1 module Dim. 98x143x50 mm | 41141.xx ⁽³⁾ 1 module Dim. 110x167x35.8 mm | 41151.xx ⁽³⁾ 1 module Dim. 110x167x70.6 mm | |
| | | 0 push b. | 1 push b. | 2 push b. | 1 push b. | 4 push b. | 0 push b. | 1 push b. | 2 push b. | 1 push b. | 4 push b. | 5 push b. | 2 push b. | 10 push b. | | | | | | | | | | | |
| | | Pixel Heavy front modules | | | | | | | | Pixel Heavy front modules | | | | | | | | Pixel Heavy installation | | | | | | | |
| | | For 41000 | | | | 41200 | | 41201 | 41202 | 41204 | 41270 | | 41271 | 41272 | 41274 | 41223 | 41225 | 41230 | 41215 | | 41218 | 41219 | 41219 | | |
| | | For 41002 | | | | 41210 | 41211 | 41212 | 41214 | | | | | | | | | | | 41221 Blank front | 41231 1 module Dim. 99.6x163 mm | 40291 1 module Dim. 82.4x144x50 mm | | | |
| Pixel Heavy | | Max 4 ⁽²⁾ | 1 | | | | | | | | | | | | | | | | 1 | | 1 | | 1 | | |
| | | Max 14 ⁽²⁾ | 1 | | | | | | | | Max 1 | | | | Max 1 | | Max 1 | | Max 1 | | 2 | | 2 | | |
| | | Max 24 ⁽²⁾ | 1 | | | | | | | | Max 2 | | | | Max 2 | | Max 1 | | Max 1 | | 3 | | 3 | | |

¹ Electronic unit 41000 allows a maximum of 54 calls and cannot be used in conjunction with electronic units 41018 and 41019.² Maximum number of calls that can be made using traditional push buttons. The use of electronic units 41018-41019 allows up to 6400 calls.³ Replace "xx" with 01: grey, 02: slate grey, 03: white and 04: anodised grey.

Replace "yy" with 01: grey, 02: slate grey, 03: white.

⁴ The number of blank modules/blank fronts is complementary to the number of buttons/front modules.

Accessory - Electronic unit wiring



Pixel and Pixel Heavy series.

Pixel and Pixel Heavy series entrance panel composition table

| Composition | Number of calls | Electronic units | | | | | Electronic expansion units | | | | | | | Installation | | | | | | | | |
|-------------|-----------------|---|---|---|--|---|---|---|---|---|---|---|---|---|---|---|---|--|---|---|---|---|
| | | Audio | | | Audio/video | | Push buttons | | Name plates | LCD display | Alphanumeric keyboard | Access control keyboard | Digital fingerprint reader | Transponder reader | Blank front ⁽⁴⁾ | Mounting frame and cover plate | Boxes and accessories | | | | | |
| | | 41000 ⁽¹⁾ Basic | 41002 With teleloop and camera input | 41005 With teleloop and wide-angle camera | 41010 10 buttons in a double row | 41015 Name plates/ address number | 41018 | 41019 | 41020 | 41016 | 41017 | Flush mounting | Rain-proof frame (optional) | Surface mounting | Mounting boxes | Rain-proof frame (optional) | Surface mounting | | | | | |
| Pixel | | Pixel front modules | | | | | | | Pixel front modules | | | | | | | Pixel installation | | | | | | |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  | | | | | |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  | | |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  | |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  | | |
| Pixel Heavy | | Pixel Heavy front modules | | | | | | | Pixel Heavy front modules | | | | | | | Pixel Heavy installation | | | | | | |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |
| | |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |  |
| | |  |  |  |  |  |  |  |  |  |  |  | <img alt="Pixel Heavy front module 41215" data-bbox="805 7 | | | | | | | | | |


Pixel and Pixel Heavy series.

Pixel and Pixel Heavy series entrance panel composition table


| Composition | | Electronic units | | | | | Electronic expansion units | | | | | | | Installation | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|--|---|---|--------------------------------------|---|--|---|----------------------------------|--|--|--|---|-------------|---|-------------------------|---|--------------------|---|--------------------------------|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|---|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|
| 3-module entrance panel | Number of calls | Audio | | Audio/video | | | Push buttons | | | | Name plates | LCD display | Alphanumeric keyboard | Access control keyboard | Digital fingerprint reader | Transponder reader | Blank front ⁽⁴⁾ | Mounting frame and cover plate | Boxes and accessories | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | 41000 ⁽¹⁾ Basic | 41002 With teleloop and camera input | 41005 With teleloop and wide-angle camera | | | 41010 10 buttons in a double row | | | | 41015 Name plates/ address number | 41018 | 41019 | 41020 | 41016 | 41017 | Mounting boxes | Rain-proof frame (optional) | Surface mounting | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Pixel | Pixel front modules | | | | | | | | | | Pixel front modules | | | | | | | Pixel installation | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|  |  |  | |  | |  | | | | |  | |  | |  | |  | |  | |  | |  | |  | |  | |  | |  | |  | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | <img alt="41199 module icon." data-bbox="5405 350 5435 390 |

Pixel Up Series

Pixel Up series entrance panel installation



Height of installation and recording range of entrance panels



Pixel Up Series


Pixel Up series entrance panel composition table

| Number of calls | Entry panels | | Accessories | Installation | | |
|-----------------|--|-------------|---|-----------------------|------------------|--|
| | Cover plate + electronic unit + flush mounting box | | | Boxes and accessories | | |
| | Audio | Audio/video | | Flush mounting | Surface mounting | |
| 6400 | | | 40425 40405 Cover plate dim. 145x405x3 mm Flush mounting box dim. 124x382x60 mm | As standard | | |
| | | | | | | |
| | | | | | | |
| 6400 | | | 40424 40404 Cover plate dim. 145x460x3 mm Flush mounting box dim. 124x437x60 mm | As standard | | |
| | | | | | | |
| | | | | | | |
| | | | 41022 | | | |


Patum series

Patum series entrance panel installation


Fixing the electronic unit to the frame




Fixing to the flush mounting box




Fixing the cover plate




Side-by-side positioning of several flush mounting boxes



Cover plates placed side-by-side



Height of installation and recording range of entrance panels



Patum series


Patum series 2-, 3- and 4-module entrance panel composition table

| Composition | 2-module entrance panels | | | | | 3-module entrance panels | | 4-module entrance panels | | Installation |
|-------------------------|--------------------------|-----------------------|-----------------------|-----------------------|-------------------------------|-------------------------------|-------------------------------|--------------------------|-------------------------------|-------------------------------|
| | Number of calls | Push buttons | | Alphanumeric | | Push buttons | Audio electronic unit | Suppl. | 4 push b. | |
| 13F3.B 12TS.B 13A4.B.43 | | | | | | | | | | |
| 41601 | 41602 | 41603 | 41604 | 41643 | 41640 | 41642 | 41606 | 41608 | 41610 | 41612 |
| 1 push b. | 2 push b. | 3 push b. | 4 push b. | 8 push b. | Audio/video electronic units | Suppl. | Audio/video electronic units | Suppl. | Audio/video electronic units | |
| 13F5.B 12TS.B 13A7.B.43 | 41621 | 41622 | 41623 | 41624 | | | | | Audio/video electronic units | |
| With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons | With 4+4 push buttons |
| 41621 | 41622 | 41623 | 41624 | 41643 | 41641 | 41642 | 41626 | 41628 | 41630 | 41632 |
| 1 push b. | 2 push b. | 3 push b. | 4 push b. | 8 push b. | 2 modules Dim. ⁽²⁾ | 3 modules Dim. ⁽³⁾ | 4 modules Dim. ⁽⁴⁾ | | 2 modules Dim. ⁽²⁾ | 3 modules Dim. ⁽³⁾ |
| Max 4 ⁽¹⁾ | 1 | 0 | 1 | 0 | | | 0 | 0 | 0 | 0 |
| Max 6 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 |
| Max 8 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 1 |
| Max 10 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 |
| Max 12 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 |
| Max 12 ⁽¹⁾ | | | | | | | | | | |
| Max 20 ⁽¹⁾ | | | | | | | | | | |
| Max 28 ⁽¹⁾ | | | | | | | | | | |


¹ Maximum number of calls that can be made using traditional push buttons. The use of electronic units 13A4.B.43 or 13A7.B.43 allows up to 6400 calls.² Dimensions of 2-module cover plate: 119.8x334x4 mm. Dimensions of 2-module flush mounting box: 99.9x270.2x60.6 mm.³ Dimensions of 3-module cover plate: 119.8x448x4 mm. Dimensions of 3-module flush mounting box: 99.9x384.7x60.6 mm.⁴ Dimensions of 4-module cover plate: 119.8x563x4 mm. Dimensions of 4-module flush mounting box: 99.9x499.2x60.6 mm.

Steely series


Steely series entrance panel installation




Side-by-side positioning of several flush mounting boxes



Cover plates placed side-by-side



Height of installation and recording range of entrance panels



Steely series



Steely series 2-, 3- and 4-module entrance panel composition table

| Composition | | 2-module entrance panels | | | | 3-module entrance panels | | 4-module entrance panels | | Installation | | | | | | |
|-------------------------------|-----------|--------------------------|-----------|------------------------------|---|--------------------------|--|------------------------------|-------------------------------|--------------|------------|-------------------------------|-------------------------------|-------------------------------|---|---|
| | | Number of calls | | Push buttons | | Alphanumeric | | Push buttons | | | | | | | | |
| | | | | Audio electronic unit | | Suppl. | | Audio electronic unit | | | | | | | | |
| | | 13F3.B | 12TS.B | 13A4.B | | | | 13F3.B | | | | | | | | |
| | | With 4+4 push buttons | | | | 4 push b. | With keyboard and alphanumeric display | | With 4+4 push buttons | | | | | | | |
| 41501 | 41502 | 41503 | 41504 | 41543 | | 41540 | 41642 | 41506 | 41508 | 41510 | 41512 | 41592 | 41593 | 41594 | | |
| 1 push b. | 2 push b. | 3 push b. | 4 push b. | 8 push b. | | | | 6 push b. | 8 push b. | 10 push b. | 12 push b. | | | | | |
| Audio/video electronic units | | Suppl. | | Audio/video electronic units | | Suppl. | | Audio/video electronic units | | | | | | | | |
| | | 13F5.B | 12TS.B | 13A7.B | | | | 13F5.B | | | | | | | | |
| | | With 4+4 push buttons | | | | 4 push b. | With keyboard and alphanumeric display | | With 4+4 push buttons | | | | | | | |
| 41521 | 41522 | 41523 | 41524 | 41543 | | 41541 | 41542 | 41526 | 41528 | 41530 | 41532 | 41592 | 41593 | 41594 | | |
| 1 push b. | 2 push b. | 3 push b. | 4 push b. | 8 push b. | | | | 6 push b. | 8 push b. | 10 push b. | 12 push b. | | | | | |
| 2 modules Dim. ⁽²⁾ | | | | | | | 3 modules Dim. ⁽³⁾ | | 4 modules Dim. ⁽⁴⁾ | | | 2 modules Dim. ⁽²⁾ | 3 modules Dim. ⁽³⁾ | 4 modules Dim. ⁽⁴⁾ | | |
| Max 4 ⁽¹⁾ | 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | | | |
| Max 6 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 1 | 0 | | | |
| Max 8 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 1 | 0 | | | |
| Max 10 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 1 | | |
| Max 12 ⁽¹⁾ | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 1 | | |
| Max 12 ⁽¹⁾ | | | | | | | 1 | 1 | 1 | 0 | 0 | 0 | 2 | 0 | 0 | |
| Max 20 ⁽¹⁾ | | | | | | | 1 | 2 | 1 | 2 | 0 | 0 | 0 | 3 | 0 | 0 |
| Max 28 ⁽¹⁾ | | | | | | | 1 | 3 | 1 | 3 | 0 | 0 | 0 | 4 | 0 | 0 |


¹ Maximum number of calls that can be made using traditional push buttons. The use of electronic units 13A4.B.43 or 13A7.B.43 allows up to 6400 calls.² Dimensions of 2-module cover plate: 119.8x299.5x4 mm. Dimensions of 2-module flush mounting box: 99.9x270.2x60.6 mm.³ Dimensions of 3-module cover plate: 119.8x414x4 mm. Dimensions of 3-module flush mounting box: 99.9x384.7x60.6 mm.⁴ Dimensions of 4-module cover plate: 119.8x528.5x4 mm. Dimensions of 4-module flush mounting box: 99.9x499.2x60.6 mm.

1300 Series

1300 series entrance panel installation





Height of installation and recording range of entrance panels



1300 Series

1300 series 2-module entrance panel composition table

| Composition | | Electronic units | | | | | | Installation | | |
|---|---|---|---|---|---|---|-----------------------|---|---|---|
| 2-module entrance panel | Number of calls | Push buttons | | | Alphanumeric | | | Boxes and accessories | | |
| | | Audio | Audio/video | Supplm. | Audio | Audio/video | Supplm. | Flush mounting | Surface mounting | |
| | |  |  |  |  |  | | Mounting boxes | Rain-proof frame (optional) | |
|  |  |  |  |  |  |  | | | | |
| | | 13F3 | 13F5 | 12TS | 13F4 | 13F7 | With 4+4 push buttons | 4 push buttons | With keyboard and alphanumeric display | |
| | | 1300 cover plates | | | | | | | | |
| | |  |  |  |  | | |  |  | |
| | | 1321 | 1358 | 132D | 132N | | |  |  | |
| | | 2 modules Dim. 100x272x22 mm | | | | | |  |  | |
| | | Buttons and blank module | | | | | |  |  | |
| | |  |  | | | | |  |  | |
| | | R131 (max 3) Push button | R130 (max 8) Blank module | | | | | | | |
| | | max 4 push buttons | max 8 push buttons | | | | | | | |
|  | Max 4 ^(t) | 1 | 0 | 1 | 0 | 1 | 1 | 1 | 1 | 1 |
|  | Max 12 ^(t) | 1 | 1 | 1 | 1 | 1 | 2 | 1 | 1 | 1 |
|  | Max 20 ^(t) | 1 | 2 | 1 | 2 | 3 | 1 | 1 | 1 | 1 |
|  | Max 28 ^(t) | 1 | 3 | 1 | 3 | 4 | 1 | 1 | 1 | 1 |

¹ Maximum number of calls that can be made using traditional push buttons. The use of electronic units 13F4 or 13F7 allows up to 6400 calls.

1300 Series


1300 series 3-module entrance panel composition table

| Composition | | Electronic units | | | | | | Installation | | |
|-------------------------|---------------------|-----------------------------|-------------------------------|--|--------------|-------------|---|---|---|------------------|
| 3-module entrance panel | Number of calls | Push buttons | | | Alphanumeric | | | Boxes and accessories | | Surface mounting |
| | | Audio | Audio/video | Suppl. | Audio | Audio/video | Suppl. | Mounting boxes | Rain-proof frame (optional) | |
| | | | | | | | | | | |
| | | 13F3 | 13F5 | 12TS | 13F4 | 13F7 | | | | |
| | | With 4+4 push buttons | 4 push buttons | With keyboard and alphanumeric display | | | | | | |
| | | 1300 cover plates | | | | | | | | |
| | | | | | | | | | | |
| | | | | | | | C321 (2 modules). Dim. 120x402x39 mm | S321 (2 modules). Dim. 120x402x74 mm | | |
| | | | | | | | | | | |
| | | | | | | | C322 (2x2 modules). Dim. 220x402x39 mm | S322 (2x2 modules). Dim. 220x402x74 mm | | |
| | | | | | | | | | | |
| | | | | | | | C323 (2x3 modules). Dim. 320x402x39 mm | S323 (2x3 modules). Dim. 320x402x74 mm | | |
| | | | | | | | | | | |
| | | | | | | | 9193 (3 modules). Dim. 98x365x50 mm | C324 (2x4 modules). Dim. 420x402x39 mm | S324 (2x4 modules). Dim. 420x402x74 mm | |
| | | Buttons and blank module | | | | | | | | |
| | | | | | | | | | | |
| | | R131 (max 7) Push button | R130 (max 11) Blank module | | | | | | | |
| | | max 8 push buttons | max 12 push buttons | | | | | | | |
| | Max 8 ^② | 1 | 0 | 1 | 0 | 1 | 1 | 1 | | |
| | Max 20 ^② | 1 | 1 | 1 | 1 | 2 | 1 | 1 | | |
| | Max 32 ^② | 1 | 2 | 1 | 2 | 3 | 1 | 1 | | |
| | Max 44 ^② | 1 | 3 | 1 | 3 | 4 | 1 | 1 | | |

^② Maximum number of calls that can be made using traditional push buttons. The use of electronic units 13F4 or 13F7 allows up to 6400 calls.


1300 Series

13K1 cover plate installation




1300/E series

40151 and 40152 cover plate installation



Height of installation and recording range of entrance panels



1300 Series

13K1 entrance panel composition table

| Composition | | Electronic units | | | Installation | |
|-------------------------|-----------------|---|---|---|------------------------------------|------------------|
| 1-module entrance panel | Number of calls | Push buttons | | Boxes and accessories | | |
| | | Audio | Audio/video | Push buttons | Flush mounting | Surface mounting |
| | | | | Mounting box with rain-proof frame | Mounting box with rain-proof frame | |
| | |  |  | | | |
| | | 13F1 | 13F2.1 | | | |
| | | With 2 push buttons | | | | |
| | | 1300 cover plates | | Additional push button | | |
| | |  | |  | | |
| | | 13K1 | R131 (max 1) | Cover plate dim.: 101x173x25 mm Flush mounting box dim.: 96x167x38 mm | Cover plate dim.: 101x173x40 mm | |
| | 1 | 1 | 0 | | | |
| | 2 | 1 | 1 | | | |

1300/E series

1300/E series entrance panel composition table

| Composition | | Electronic units | | | Installation | |
|-------------------------|-----------------|---|---|---|---|--|
| 1-module entrance panel | Number of calls | Push buttons | | | Boxes and accessories | |
| | | Audio | Audio/video | Push buttons | Flush mounting | Surface mounting |
| | | | | | Mounting box with rain-proof frame | Mounting box with rain-proof frame |
| | |  |  | | | |
| | | 40131 | 40135 | | | |
| | | With 2 push buttons | | | | |
| | | 1300/E cover plates | | | | |
| | |  |  |  |  | |
| | | 40141 | 40142 | 40151 | 40152 | Cover plate dim.: 101x173x25 mm Flush mounting box dim.: 96x167x38 mm |
| | 1 | 1 | 0 | 1 | 0 | |
| | 2 | 0 | 1 | 0 | 1 | Cover plate dim.: 101x173x40 mm |

Outdoor stations for Pixel, Pixel Heavy and Pixel Up cover plates

Audio/video and audio electronic units

41005
Audio/video unit
with wide-angle
and teleloop41002
Audio unit with
wide-angle and
video input41000
Audio unit

| Technical characteristics: | 41005 | 41002 | 41000 |
|---|-------------------------------------|-------------------------------------|-------------------------------------|
| Camera | CCD 1/4" with output PAL/CVBS | | |
| Resolution | 512 TVL | | |
| Viewing angles (horizontal/vertical) | 104°/83° | | |
| Minimum lighting | 0.1 lux | | |
| Power supply | From BUS 28 VDC rated 21 VDC min | From BUS 28 VDC rated 21 VDC min | From BUS 28 VDC rated 21 VDC min |
| Absorption: | | | |
| in standby | 40 mA | 40 mA | 25 mA |
| in communication | 200 mA | 130 mA | 120 mA |
| in communication and lock activation | 250 mA | 180 mA | 180 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA | 50 mA | |
| Absorption for additional module power supply | 130 mA max | 130 mA max | 130 mA max |
| Max modules 41010 | 8 | 8 | 5 |
| Video signal output | 16 dBm at 100 Ohm | | |
| Operating temperature | -25 °C ~ +55 °C | -25 °C ~ +55 °C | -25 °C ~ +55 °C |
| Ambient class | A2 | A2 | A2 |

The maximum current delivered to the additional electronic modules is 500 mA at 5 VDC.

Additional electronic modules

41010
10 buttons
in 2 rows41015
Unit with name
panel backlit41016
Fingerprint
reader41017
Transponder
reader41018
3,5" display41019
Alphanumeric
keypad

| Additional electronic module absorption: | | | | | |
|--|--------------|--------------------------------|-------------------------------|-------------------------------|--------------|
| | 41010 | 41015 | 41016 | 41017 | 41018 |
| Type of module | Push buttons | Name plates/ address number | Digital fingerprint reader | Digital fingerprint reader | 3.5" display |
| Absorption at 5 VDC | 60 mA | 60 mA | 260 mA | 250 mA | 220 mA |

| | 41019 |
|-----------------------|--------------------------|
| Type of module | Alphanumeric keyboard |

| | 90 mA |
|--------------------------------|-------|
| Absorption at 5 VDC | |

Outdoor stations for Pixel, Pixel Heavy and Pixel Up cover plates

Audio/video and audio entrance panels

40405
Pixel Up audio/video
entrance panel,
stainless steel40404
Pixel Up audio/video
entrance panel with
4x4 hole for
reader, stainless
steel40425
Pixel Up audio entrance
panel,
stainless steel13F5
13F5.B
Audio/video unit
with 8-button.
Backlighting:
green LED (13F5) or
white LED (13F5.B)13F3
13F3.B
Audio unit
with 8-button.
Backlighting:
green LED (13F3) or
white LED (13F3.B)

| Technical characteristics: | 40405/40404 | 40425/40424 |
|---|--|--|
| Camera | CCD 1/4" with output PAL/CVBS | |
| Resolution | 512 TVL | |
| Viewing angles (horizontal/vertical) | 104°/83° | |
| Minimum lighting | 0.1 lux | |
| Power supply | From BUS 28 VDC rated 21 VDC min | From BUS 28 VDC rated 21 VDC min |
| Absorption: | | |
| in standby | 120 mA | 120 mA |
| in communication | 280 mA | 280 mA |
| in communication and lock activation | 330 mA | 330 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA | 50 mA |
| Absorption for additional module power supply | 50 mA max | 50 mA max |
| Video signal output | 16 dBm at 100 Ohm | |
| Operating temperature | -25 °C ~ +55 °C | -25 °C ~ +55 °C |
| Ambient class | A2 | A2 |
| Indoor/outdoor use | Outdoor | Outdoor |
| IP protection degree | IP54 | IP54 |
| IK protection degree | IK08 | IK08 |
| Dimensions (W x H x D) | 145 x 460 x 63 mm (thickness of cover plate flush with wall 3 mm) | 145 x 460 x 63 mm (thickness of cover plate flush with wall 3 mm) |

Video and audio door entry systems: outdoor stations

Outdoor stations for Pixel, Pixel Heavy and Pixel Up cover plates

Audio/video and audio electronic units with alphanumeric call



13F7
13F7.B
Audio/video unit with stainless steel keypad. Backlighting: green LED (13F7) or white LED (13F7.B)

13A7.B
Audio/video unit with stainless steel keypad. White LED backlighting

13A7.B.43
Audio/video unit with golden finish stainless steel keypad. White LED backlighting



13F4
13F4.B
Audio unit with stainless steel keypad. Backlighting: green LED (13F4) or white LED (13F4.B)

13A4.B
Audio unit with stainless steel keypad. White LED backlighting

13A4.B.43
Audio unit with golden finish stainless steel keypad. White LED backlighting

Additional electronic modules



12TS
12TS.B
Unit with 4-button. Backlighting: green LED (12TS) or white LED (12TS.B)

12TD
Unit with 4-button. Green LED backlighting

Additional electronic module absorption:


| | 12TS | 12TS.B | 12TD |
|-----------------------------|---|---|---|
| Type of module | 4 push buttons (Green LED backlighting) | 4 push buttons (White LED backlighting) | 8 push buttons (Green LED backlighting) |
| Absorption at 12 VDC | 7 mA | 7 mA | 7 mA |

Maximum 5 additional modules

Video and audio door entry systems: outdoor stations

Outdoor stations for 1300 and 1300/E series cover plates for one-family/two-family kits

Audio/video and audio electronic units



13F2.1
Audio/video unit for 13K1 plate



13F1
Audio unit for 13K1 plate

| Technical characteristics: | | 13F2.1 | 13F1 |
|---|-------------------------------|---------------------|-------------|
| Camera | CCD 1/4" with PAL/CVBS output | | |
| Resolution | 500 TV lines | | |
| Viewing angles (horizontal/vertical) | 100°/82° | | |
| Minimum lighting | 1.0 lux | | |
| Power supply | From BUS min 24 VDC | From BUS min 24 VDC | |
| Absorption: | | | |
| in standby | 40 mA | 40 mA | |
| in communication | 250 mA | 250 mA | |
| in communication and lock activation | 350 mA | 350 mA | |
| Max residual absorption with additional power supply unit 6923 | 50 mA | 50 mA | |
| Video signal output | 16 dBm at 100 Ohm | | |
| Operating temperature | -25 °C ~ +55 °C | -25 °C ~ +55 °C | |
| Ambient class | A2 | A2 | |



40135
Audio/video unit for 40151 and 40152 plate



40131
Audio unit for 40141 and 40152 plate

| Technical characteristics: | | 40135 | 40131 |
|---|--------------------------------|---------------------|--------------|
| Camera | CMOS 1/4" with PAL/CVBS output | | |
| Resolution | 380 TV lines | | |
| Viewing angles (horizontal/vertical) | 100°/82° | | |
| Minimum lighting | 1.0 lux | | |
| Power supply | From BUS min 24 VDC | From BUS min 24 VDC | |
| Absorption: | | | |
| in standby | 40 mA | 25 mA | |
| in communication | 200 mA | 80 mA | |
| in communication and lock activation | 250 mA | 140 mA | |
| Video signal output | 16 dBm at 100 Ohm | | |
| Operating temperature | -25 °C ~ +55 °C | -25 °C ~ +55 °C | |
| Ambient class | A2 | A2 | |

Outdoor stations for 8000 series cover plates and letterbox entrance panels

Audio and video electronic units



6931
Audio unit



6932
Audio unit for kit

| Technical characteristics: | | 6931 | 6932 |
|--------------------------------------|---------------------|---------------------|-------------|
| Power supply | From BUS min 24 VDC | From BUS min 24 VDC | |
| Absorption: | | | |
| in standby | 60 mA | 60 mA | |
| in communication | 265 mA | 265 mA | |
| in communication and lock activation | 415 mA | 415 mA | |
| Operating temperature | -25 °C ~ +55 °C | -25 °C ~ +55 °C | |
| Ambient class | A2 | A2 | |



657C
Colour video unit

| Technical characteristics: | | 657C |
|---|-------------------------------|-------------|
| Camera | CCD 1/4" with PAL/CVBS output | |
| Resolution | 380 TV lines | |
| Viewing angles (horizontal/vertical) | 72°/58° | |
| Minimum lighting | 1 lux | |
| Power supply | From BUS rated 28 VDC | |
| Absorption: | | |
| in standby | 20 mA | |
| in communication | 180 mA | |
| Max residual absorption with additional power supply unit 6923 | 50 mA | |
| Video signal output | 10 dBm at 100 Ohm | |
| Operating temperature | -5 °C ~ +50 °C | |
| Ambient class | A2 | |

INDOOR STATIONS.


Communicating is simple, effective and safe.

The **indoor video door entry system** stations - hands-free or with a handset - stand alone or integrated in the By-me Plus home automation system, feature exquisite, modern, prized finishes and are thinner than traditional devices.



● **Tab Free 4.3 video entryphones** - with 4.3" display are designed to communicate with the outside in complete freedom while keeping your hands free and providing a generous view of the world outside your home. A **compact and stylish video entryphone**, with gentle silhouettes that soften the corners and extend across the entire smooth, glass-like surface.

● **Tab 7S Up and 5S Up video entryphones** - inspired by the light weight and simple silhouettes that distinguish all the models in the Tab series, affording revolutionary functions teamed with stylish design. In addition to traditional video door entry functions, **Tab 7S Up and 5S Up - thanks to the integrated Wi-Fi** and to the Video Door app - allow **call repetition on your smartphone**, ensuring total control even when you are out and about. In short, this is a product with its sights set firmly on the future.



● **Tab jr. ENTRYPHONES** - for those who don't need the video function. It is an audio entryphone device only offering the same technology, quality, design and standard functions of the Tab 4.3 "bigger" version.

● **Tab 4.3 video entryphones** - with 4.3" display and a thin profile just 2.6 cm thick, for surface mounting, and up to 2 cm for the Tab video entryphone, thanks to a special mounting frame for semi-flush mounting.


Summary table of video door entry indoor station functionality

| | Tab 7S Up | | Tab 5S Up | | Tab 7 | Tab Free 4.3 | Tab 4.3 | |
|--|---|---|--|---|---|---|---|---|
| Series |  |  |  |  |  |  |  |  |
| Code | 40517 | 40517.04 | 40515 | 40515.04 | 40505 | 7559 | 7558 | 7549 |
| Type | Hands-free | | Hands-free | | Hands-free | Hands-free | Handset | Handset |
| Display | 7" Touch 1024x600 | | 5" 800x480 | | 7" 800x480 | 4.3" 480x272 | 4.3" 480x272 | 4.3" 480x272 |
| Button type | Capacitive | | Capacitive | | Capacitive | Capacitive | Capacitive | Capacitive |
| User interface | GUI | | GUI | | GUI | OSD | OSD | - |
| Call forwarding to smartphone or tablet | ✓ | | ✓ | | - | - | - | - |
| Lock release | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Auxiliary controls | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Self-start/cyclic operation | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Intercom | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Landing call | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Switchboard call | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Alert function | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Teleloop for hearing aids | ✓ | | ✓ | | ✓ | ✓ | ✓ | ✓ |
| Professional firm function | ✓ | | ✓ | | - | ✓ | - | - |
| Voice mail | ✓ | | ✓ | | - | - | - | - |
| Colour | White | Black | White | Black | White | White | White | White |
| Installation | Flush mounting | Only for semi-flush mounting box 40591 | | Only for semi-flush mounting box 40590 | | - | - | Only for flush mounting box 4+4, V71318 or 6149 |
| | Surface mounting | With Vimar flush mounting box V71701 or V71303 or V71703 or 71318 or V71718 | | With Vimar flush mounting box V71701 or V71303 or V71703 or 71318 or V71718 or 6149 | | With Vimar flush mounting box V71701 or V71303 or V71703 or 71318 or V71718 or 6149 | ✓ | ✓ |
| | Table mounting | With base 40596 | | With base 40595 | | With base 40195 | With base 753A+753B | With base 753A+753B |



View app available from the Vimar website or Apple Store and Google Play

Summary table of door entry indoor station functionality

| | Tab jr. | | Voxie | | |
|------------------------------------|---|---|---|---|---|
| Series |  |  |  |  |  |
| Code | 7509 | 7509/D | 40540 | 40542 | 40547 |
| Type | Handset | Handset | Handset | Handset | Hands-free |
| Button type | Capacitive | Capacitive | Mechanical | Mechanical | Mechanical |
| Lock release | ✓ | ✓ | ✓ | ✓ | ✓ |
| Auxiliary controls | ✓ | ✓ | ✓ | ✓ | ✓ |
| Self-start/cyclic operation | ✓ | ✓ | - | - | - |
| Intercom | ✓ | ✓ | - | ✓ | ✓ |
| General intercom call | - | - | - | ✓ | ✓ |
| Landing call | ✓ | ✓ | ✓ | ✓ | ✓ |
| Switchboard call | ✓ | ✓ | ✓ | ✓ | ✓ |
| Alert function | ✓ | ✓ | ✓ | ✓ | ✓ |
| Teleloop for hearing aids | - | ✓ | - | - | ✓ |
| Professional firm function | - | - | ✓ | ✓ | ✓ |
| "Paging" function | - | - | - | ✓ | ✓ |
| Colour | White | White | White | White | White |
| Installation | Surface mounting | ✓ | ✓ | ✓ | ✓ |
| | Table mounting | With base 753A+753B | With base 753A+753B | With base 40598 | With base 40598 |

Hands-free video indoor stations

Tab 7S Up - Video entryphone



40517
Hands-free video entryphone with Wi-Fi, white
40517.04
Hands-free video entryphone with Wi-Fi, black

| Technical characteristics: 40517 and 40517.04 | |
|--|---|
| Display | 7" 16:9 LCD Touch Screen, 1024 x 600 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 5 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 58 mA |
| maximum current | 480 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Wi-Fi: | |
| frequency bands | 802.11 b, g, n, 2.4 GHz |
| frequency range and RF transmission power | 2412 - 2472 MHz, < 100 mW (20 dBm) |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 189 x 171 x 24.4 mm (semi-flush thickness 13.1 mm) |

Mounting: from semi-flush mounting on masonry walls or hollow walls with Vimar flush mounting box 40591, to surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) horizontal and vertical, 4+4 modules (Vimar V71318, V71718 or Elvox 6149) and square British standard. Table mounting with Vimar accessories 40596

Tab 7 - Video entryphone



40505
Hands-free video entryphone

| Technical characteristics: 40505 | |
|--|---|
| Display | 7" 16:9 LCD, 800 x 480 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 7 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 25 mA |
| maximum current | 350 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 165.8 x 184 x 25 mm |

Mounting: surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) horizontal and vertical, 4+4 modules (Vimar V71318, V71718) and square British standard. Table mounting with Vimar accessories 40195, 753B

Tab 5S Up - Video entryphone



40515
Hands-free video entryphone with Wi-Fi, white
40515.04
Hands-free video entryphone with Wi-Fi, black

| Technical characteristics: 40515 and 40515.04 | |
|--|--|
| Display | 5" 16:9 LCD Touch Screen, 800 x 480 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 5 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 55 mA |
| maximum current | 420 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Wi-Fi: | |
| frequency bands | 802.11 b, g, n, 2.4 GHz |
| frequency range and RF transmission power | 2412 - 2472 MHz, < 100 mW (20 dBm) |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 148 x 158 x 24.4 mm (semi-flush thickness 13.1 mm) |

Mounting: from semi-flush mounting on masonry walls or hollow walls with Vimar flush mounting box 40590, to surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) horizontal and vertical, 4+4 modules (Vimar V71318, V71718 or Elvox 6149) and square British standard. Table mounting with Vimar accessories 40595

Hands-free video indoor stations

Tab Free 4.3 - Video entryphones



7559
Hands-free video entryphone with intercom calls
7558
Hands-free video entryphone

| Technical characteristics: 7558 and 7559 | |
|--|---|
| Display | 4.3" 16:9 LCD, 480 x 272 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 7 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 17 mA |
| maximum current | 280 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 155 x 145 x 23.5 mm |

Mounting: surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) or vertical and square British standard. Table mounting with Vimar accessories 753A, 753B

Video indoor stations with handset


Tab 4.3 - Video entryphones



7549
Video entryphone with handset and intercom calls
7548
Video entryphone with handset

| Technical characteristics: 7549 and 7548 | |
|--|--|
| Display | 4.3" 16:9 LCD, 480 x 272 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 12 (7549) / 8 (7548) capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 18 mA |
| maximum current | 180 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 160 x 180 x 45.4 mm |

Mounting: surface with wall plugs or in round flush mounting box ø 60 mm (Vimar V71701) or 3 modules (Vimar V71303, V71703). Table mounting with Vimar accessories 753A, 753B



View app available from the Vimar website or Apple Store and Google Play



All video indoor stations are fitted with an integrated induction coil for wearers of hearing aids fitted with T-Coil to be able to hear.

Hands-free audio indoor stations

Voxie - Entryphones

40547
Hands-free entryphone
with 7-button

| Technical characteristics: 40547 | |
|---|--|
| Keyboard | 7 mechanical buttons |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 10 mA |
| peak current with ringtone in operation | 140 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies for entrance panel, landing and intercom calls. |
| Dimensions | 95 x 146 x 19.8 mm |
| Mounting: surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) vertical, 4+4 modules (Vimar V71318, V71718) and square British standard. Table mounting with Vimar accessories 40598 | |

Audio indoor stations with handset

Tab jr. - Entryphones

7509
7509/D
Entryphone with
handset

| Technical characteristics: 7509 and 7509/D | |
|---|---|
| Keyboard | 8 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 7 mA |
| peak current with ringtone in operation | 100 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 105 x 179.3 x 40 mm |
| Mounting: surface with wall plugs or in 3-module flush mounting box (Vimar V71303, V71703) or 60 or 70 mm round mounting box. Table mounting with the desktop base accessory 753A and the interconnecting stud 753B (sold separately) | |

Voxie - Entryphones

40540
40540.D
Entryphone
with handset
and 2-button40542
Entryphone
with handset
and 6-button

| Technical characteristics: 40540, 40540.D and 40542 | |
|---|--|
| Keyboard | 2 (40540 and 40540.D) / 6 (40542) mechanical buttons |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 10 mA |
| peak current with ringtone in operation | 100 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies for entrance panel, landing and intercom calls. |
| Dimensions | 95 x 200 x 28.5 mm |
| Mounting: surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) vertical, 4+4 modules (Vimar V71318, V71718) and square British standard. Table mounting with Vimar accessories 40598 | |



Versions entryphones 40540, 40540.D and 7509/D are fitted with an integrated induction coil for wearers of hearing aids fitted with T-Coil to be able to hear.

Porter switchboards

Switchboards

40510
Porter switchboard with
7" display

| Technical characteristics: 40510 | |
|--|--|
| Display | 7" LCD 16:9, 800x480 pixel resolution |
| Keyboard | Alphanumeric keyboard |
| Power supply | 28 VDC - via power supply unit 6923 (not supplied as standard) |
| Absorption: | |
| in standby | 86 mA |
| maximum current | 300 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 242 x 213 x 221 mm |

System components

System power supply units

40110
Power supply unit for
video door entry system

| Technical characteristics: 40110 | |
|----------------------------------|---|
| Power supply | 110 ~ 240 VAC |
| Maximum consumption | 1.2 A 100 VAC ~ 0.6 A 240 VAC |
| Dissipated power | 15 W |
| BUS output voltage | 28 VDC rated (SELV - EN60950-1) |
| Max. current output | 1.6 A (1 A continuous + 0.6 A with cycle 30 s ON - 150 s OFF) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 108 x 106 x 63 mm (6 modules DIN 60715 TH35) |

40100
Supply unit for
audio kit

| Technical characteristics: 40100 | |
|----------------------------------|--|
| Power supply | 100 ~ 240 VAC |
| Maximum consumption | 0.5 A 110 VAC ~ 0.3 A 240 VAC |
| Dissipated power | 6 W |
| BUS output voltage | 28 VDC rated (SELV - EN60950-1) |
| Max. current output | 0.66 A (0.15 A continuous + 0.51 A with cycle 60 s ON - 150 s OFF) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 108 x 106 x 63 mm (6 modules DIN 60715 TH35) |

System components

Additional power supply units



6923
6923/117
6923/120
6923/240
Supply unit with
28 VDC output



6582.1
Adjustable supply unit

Passive floor video distributor



691D
1-output
distributor



692D
4-output
distributor

Technical characteristics: 6923, 6923/120, 6923/240

| | |
|-----------------------|--|
| Power supply | 230 VAC 50/60Hz - 6923 120 VAC 50/60Hz - 6923/120 240 VAC 50/60Hz - 6923/240 |
| Maximum consumption | 107 mA (6923, 6923/240), 209 mA (6923/120) |
| Dissipated power | 6 W |
| Output voltage | 28 VDC rated (SELV - EN60950-1) |
| Max. current output | 0.5 A (0.15 A continuous + 0.35 A with cycle 30 s ON - 180 s OFF) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 119.40 x 72 x 59 mm (4 modules DIN 60715 TH35) |

Technical characteristics: 6582.1

| | |
|-----------------------|--|
| Power supply | 230 VAC 50/60Hz |
| Maximum consumption | 120 mA |
| Dissipated power | 35 VA |
| Output voltage | 10.5 VDC, 13.5 VDC and 18 VDC outputs |
| Max. current output | 0.8 A with cycle 30s ON - 90s OFF |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 119.40 x 72 x 59 mm (4 modules DIN 60715 TH35) |

Technical characteristics: 691D

| | |
|---|---|
| Video gain in pass-through output | -0.5 dB |
| Tap-off video gain | -20 dB |
| Tap-off outputs | 1 |
| Max number of distributors in cascade per riser | 20 with Elvox cable type 732x.../15 with cable CAT5 |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 36.8 x 32.4 x 13.8 mm |

Maximum output current: 700 mA (for each output supports two monitors connected in in-out which are turned on together)

Technical characteristics: 692D

| | |
|---|---|
| Power supply | From BUS rated voltage 28 VDC |
| Video gain in pass-through output | -0.5 dB |
| Tap-off video gain | -20 dB |
| Tap-off outputs | 4 |
| Max number of distributors in cascade per riser | 15 with Elvox cable type 732x.../10 with cable CAT5 |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 60 x 82 x 21 mm |

Maximum current for each output: 700 mA (for each output supports two monitors connected in in-out which are turned on together)

System components

Relay modules



69RH
Programmable
device with 2
relays



69RH/L
Programmable device
with 2 relays for calls
from the outdoor station

Technical characteristics:

69RH, 69RH/L

| | |
|-----------------------|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 15 mA |
| maximum current | 80 mA |
| Type of Contacts | 2 NO |
| Contacts rating | 230 VAC 3 A |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 70 x 92 x 50 mm (4 modules DIN 60715 TH35) |



69PH
Programmable device with
2 relays. It can be used as
a monostable relay or call
repeater

Technical characteristics:

69PH

| | |
|-----------------------|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 15 mA |
| maximum current | 40 mA |
| Type of Contacts | 2 NO/NC |
| Contacts rating | 230 VAC 3 A / AC1 |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 70 x 92 x 50 mm (4 modules DIN 60715 TH35) |



0170/101
Relay with power supply
12 VDC or VAC or
Sound System call

Technical characteristics:

0170/101

| | |
|-----------------------|--|
| Power supply | 12 VDC / VAC |
| Absorption | 80 mA (terminals 1/2-C) |
| Type of Contacts | 1 NO/NC change-over |
| Contacts rating | 230 VAC 3 A / AC1 |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 70 x 92 x 50 mm (4 modules DIN 60715 TH35) |

Separators



692S.1
Separator

Technical characteristics:

692S.1

| | |
|-----------------------------------|---|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 15 mA (main BUS) and 25 mA (secondary BUS) |
| maximum current | 40 mA (main BUS) and 50 mA (secondary BUS) |
| Video gain in pass-through output | -0.2 dB |
| Tap-off video gain | 0 dB |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 72 x 110 x 60 mm (4 modules DIN 60715 TH35) |

Video and audio door entry systems: system components

System components

Riser splitters for 4 lines

69DV
69DV/5
Riser splitter for 4 riser lines

| Technical characteristics: 69DV and 69DV/5 | |
|--|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby in the absence of video signal | 15 mA |
| maximum current | 50 mA |
| Max output current | 800 mA |
| Video gain in pass-through output | -0.2 dB |
| Tap-off video gain | 0 dB |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 119.40 x 72 x 59 mm (4 modules DIN 60715 TH35) |

69DV: riser splitter for twisted pair
69DV/5: riser splitter with CAT5 cable

Concentrator for 4 outdoor stations and 2 output risers

69MX
69MX/5
Concentrator for 4 outdoor stations in parallel

| Technical characteristics: 69MX and 69MX/5 | |
|---|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby in the absence of video signal | 25 mA |
| maximum current | 50 mA |
| Max current between OUT1 and IN1 or IN2 or IN3 or IN4 | 800 mA |
| Max current between OUT1 and OUT2 | 1500 mA |
| Minimum level of input signal | -10 dBm |
| Output level | +16 dBm |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 119.40 x 72 x 59 mm (4 modules DIN 60715 TH35) |

69MX: concentrator for twisted pair;
69MX/5: Concentrator with CAT5 cable

Expansion interface for system with 200 indoor stations

69RS.1
Expansion interface for 200 indoor stations

| Technical characteristics: 69RS.1 | |
|-----------------------------------|---|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 15 mA (main BUS) and 25 mA (secondary BUS) |
| maximum current | 40 mA (main BUS) and 50 mA (secondary BUS) |
| Video gain in output | -0.2 dB |
| Tap-off video gain | 0 dB |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 72 x 110 x 60 mm (4 modules DIN 60715 TH35) |

IoT gateway for integration of Due Fili Plus video door entry system

01415
IoT gateway for integration of Due Fili Plus video door entry system

| Technical characteristics: 01415 | |
|--|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 120 mA |
| maximum current | 300 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 109.8 x 107.7 x 59.5 mm (6 modules DIN 60715 TH35) |

Installation always requires the use of the additional power supply unit 6923, with the exception of a system comprising solely: 1 outdoor station, 1 system power supply unit, at most 2 art. 01415

Video and audio door entry systems: system components

System components

Video signal riser amplifier

692M
692M/5
Video signal riser amplifier

| Technical characteristics: 692M and 692M/5 | |
|--|-------------------------------|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby in the absence of video signal | 24 mA |
| maximum current | 48 mA |
| Max output current | 1400 mA |
| Gain | +6 dB “-“/ +14 dB “+“ |
| Max IN level with setting “-“ | 9 dBm |
| Max IN level with setting “+“ | 1 dBm |
| Protection degree: | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 60 x 82 x 21 mm |

692M: video signal riser amplifier for twisted pair
692M/5: video signal riser amplifier with CAT5 cable

Other devices

6120
Interface for 2 buttons693T
CCTV-type camera interface69AM/T
Video selector for 4 cameras

| Technical characteristics: 6120 | |
|---|-------------------------------|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby in the absence of video signal | 2 mA |
| maximum current | 10 mA |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 48 x 70 x 19 mm |

| Technical characteristics: 693T | |
|---------------------------------|---|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby | 20 mA |
| maximum current | 100 mA |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 70 x 115 x 50 mm (4 modules DIN 60715 TH35) |

Interface for connecting cameras to dedicated audio outdoor stations

| Technical characteristics: 69AM/T | |
|--|--|
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: | |
| in standby in the absence of video signal | 25 mA |
| maximum current | 50 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Video signal output | 10 dBm at 100 Ohm |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Dimensions | 139 x 114.5 x 51 mm (8 modules DIN 60715 TH35) |

| Technical characteristics: 69MD | |
|---------------------------------|---|
| Power supply | 18 VDC from power supply 6582.1 |
| Absorption: | |
| from 18 VDC | 100 mA intermittent |
| in standby | 10 mA from BUS |
| maximum current | 60 mA from BUS |
| Grado di protezione | IP30 |
| Operating temperature | -0 °C ~ +40 °C (indoor use) |
| Dimensions | 70 x 115 x 50 mm (4 modules DIN 60715 TH35) |

Interface for conversion from Due Fili Plus signal in PAL/CVBS standard video signal and audio signal

System components

Other devices



692E
Overvoltage protection device



692G
Ground divider

Electronic ringtones



860A
Electronic ringtone with 2 inputs, 230 VAC



860B
Electronic ringtone with 2 inputs, 15 VAC



860C
Electronic ringtone with 3 inputs, 12-15 VAC/VDC

System components

Programming devices



692I/U

692I/U PC USB interface for programming Due Fili Plus systems

PC interface with USB connector and 69CD software for basic and advanced programming of Due Fili devices, for apartments with more than 4 video entryphones or entryphones in a single apartment



692I

692I PC RS232 interface for programming Due Fili Plus systems

PC interface with RS232 connector and 69CD software for basic and advanced programming of Due Fili devices, for apartments with more than 4 video entryphones or entryphones in a single apartment



R963

R963 Wiring set

Complete wiring set for programmable time switch 950C and interface 692I/U

Cables



732H.E.100
732H.E.500

732H.E.100 and 732H.E.500

Due Fili Plus cable for internal laying, 2x1 mm² twisted conductors, with PVC sheath, CPR Eca class, operating temperature -25/+70 °C, not suitable for laying in underground ducting, suitable for installation with category I energy cable (U0 = 400 V), blue.
732H.E.100: 100 m bundle.
732H.E.500: 500 m coil



732I.C.100

732I.C.100

Due Fili Plus cable for internal/external laying, 2x1 mm² twisted conductors, with insulation and LSZH sheath, Cca class - s1b, d1, a1, operating temperature -25/+70 °C, insulation degree 600/1000 V, suitable for laying underground in dry ducting or channels with efficient drainage (max. 24 hrs wet), not suitable for laying directly underground, suitable for installation with category I energy cable (U0 = 400 V), purple - 100 m bundle



732I.E.100
732I.E.500

732I.E.100 and 732I.E.500

Due Fili Plus cable for internal/external laying, 2x1 mm² twisted conductors, with insulation and LSZH sheath, Eca class, operating temperature -25/+70 °C, insulation degree 600/1000 V, suitable for laying underground in dry ducting or channels with efficient drainage (max. 24hrs wet), not suitable for laying directly underground, suitable for installation with category I energy cable (U0 = 400 V), green.
732I.E.100: 100 m bundle.
732I.E.500: 500 m coil

Summary table of video door entry indoor station functionality

| | Tab 7S | Tab Free 3.5 |
|--|---|---|
| Series |  |  |
| Code | 40507 | 7539 |
| Type | Hands-free | Hands-free |
| Display | 7" Touch 800x480 | 3.5" 320x240 |
| Button type | Capacitive | Capacitive |
| User interface | GUI | - |
| Call forwarding to smartphone or tablet | ✓ | - |
| Lock release | ✓ | ✓ |
| Auxiliary controls | ✓ | ✓ |
| Self-start/cyclic operation | ✓ | ✓ |
| Intercom | ✓ | ✓ |
| Landing call | ✓ | ✓ |
| Switchboard call | ✓ | ✓ |
| Alert function | ✓ | ✓ |
| Teleloop for hearing aids | ✓ | ✓ |
| Professional firm function | ✓ | - |
| Voice mail | ✓ | - |
| Colour | White | White |
| Installation | Flush mounting | - |
| | Surface mounting | With Vimar flush mounting box V71701 or V71303 or V71703 or 71318 or V71718 |
| | Table mounting | With base 40195 |
| | | With base 753A+753B |



View app available from the
Vimar website or Apple Store
and Google Play

Summary table of door entry indoor station functionality

| | 6900 | Petrarca | 8870 |
|------------------------------------|---|---|---|
| Series |  |  |  |
| Code | 6901 | 6901/D | 6209/P |
| Type | Hands-free | Hands-free | Handset |
| Button type | Mechanical | Mechanical | Mechanical |
| Lock release | ✓ | ✓ | ✓ |
| Auxiliary controls | ✓ | ✓ | ✓ |
| Self-start/cyclic operation | ✓ | ✓ | - |
| Intercom | ✓ | ✓ | ✓ |
| General intercom call | - | - | - |
| Landing call | ✓ | ✓ | ✓ |
| Switchboard call | ✓ | ✓ | ✓ |
| Alert function | - | - | ✓ |
| Teleloop for hearing aids | - | ✓ | - |
| Professional firm function | - | - | - |
| "Paging" function | - | - | - |
| Colour | White | White | White |
| Installation | Surface mounting | ✓ | ✓ |
| | Table mounting | - | With base 6140 |

Hands-free video indoor stations

Tab 7S - Video entryphone

40507
Hands-free video entryphone with Wi-Fi

| Technical characteristics: | 40507 |
|--|--|
| Display | 7" 16:9 LCD Touch Screen, 800 x 480 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 2 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: in standby | 120 mA |
| maximum current | 400 mA |
| Max residual absorption with additional power supply unit 6923 | 50 mA |
| Wi-Fi: | |
| frequency bands | 802.11 b, g, n, 2.4 GHz |
| frequency range and RF transmission power | 2412 - 2472 MHz, < 100 mW (20 dBm) |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 165.8 x 184 x 25 mm |
| Mounting: surface mounting in round flush mounting box ø 60 mm (Vimar V71701), 3 modules (Vimar V71303, V71703) horizontal and vertical, 4+4 modules (Vimar V71318, V71718) and square British standard. Table mounting with Vimar accessories 40195, 753B | |



Audio indoor stations with handset

Petrarca - Entryphones

6209/P
6209/D

Entryphone with handset and 5-button (6209/P) or 3-button (6209/D)

| Technical characteristics: | 6209/P and 6209/D |
|---|---|
| Keyboard | 5 (6209/P) / 3 (6209/D) mechanical buttons expandable up to 9 |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: in standby | 10 mA |
| peak current with ringtone in operation | 65 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (3) |
| Dimensions | 85 x 220 x 65 mm |
| Mounting: surface with wall plugs or in 3-module flush mounting box (Vimar V71303, V71703) vertical | |

8870 series - Entryphones

8879.1
8879.1/D

Entryphone with handset

| Technical characteristics: | 8879.1 and 8879.1/D |
|---|--|
| Keyboard | 2 mechanical buttons |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: in standby | 10 mA |
| peak current with ringtone in operation | 160 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (3) |
| Dimensions | 75 x 220 x 60.5 mm |
| Mounting: surface with wall plugs or in 3-module flush mounting box (Vimar V71303, V71703) vertical | |

Tab Free 3.5 - Video entryphone

7539
Hands-free video entryphone

| Technical characteristics: | 7539 |
|---|---|
| Display | 3.5" 4:3 LCD, 320 x 240 pixel resolution |
| Minimum video signal level on the bus for reception | -20 dBm |
| Keyboard | 9 capacitive buttons with backlit symbols |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: in standby | 10 mA |
| maximum current | 160 mA |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 131 x 150 x 25.5 mm |
| Mounting: surface with wall plugs or in round flush mounting box ø 60 mm (Vimar V71701) or 3 modules (Vimar V71303, V71703). Table mounting with Vimar accessories 753A, 753B | |

Hands-free audio indoor stations

6900 series - Entryphones

6901
6901/D
Hands-free entryphone

| Technical characteristics: | 6901 and 6901/D |
|---|---|
| Keyboard | 10 mechanical buttons |
| Power supply | From BUS rated voltage 28 VDC |
| Absorption: in standby | 10 mA |
| peak current with ringtone in operation | 110 mA (6901) / 130 mA (6901/D) |
| Ambient class | A1 (indoor use) |
| Protection degree | IP30 |
| Operating temperature | -5 °C ~ +40 °C (indoor use) |
| Operating environment humidity | 10 ~ 80% (non-condensing) |
| Ringtone | Electronic with different melodies (10) |
| Dimensions | 102 x 142 x 23 mm |
| Mounting: surface with wall plugs or in round flush mounting box ø 60 mm (Vimar V71001, V71701) or 3 modules (Vimar V71303, V71703) | |

Video indoor stations and versions entryphones 6209/D, 6901/D and 8879.1/D are fitted with an integrated induction coil for wearers of hearing aids fitted with T-Coil to be able to hear.

View app available from the Vimar website or Apple Store and Google Play

System components


System power supply units

6922.1
Power supply unit for video door entry system40101
Supply unit for audio entry system


| Technical characteristics: | 6922.1 | 40101 |
|----------------------------|---|---|
| Power supply | 110 ~ 240 VAC | 110 ~ 240 VAC |
| Maximum consumption | 1 A 110 VAC ~ 0.6 A 240 VAC | 0.7 A 110 VAC ~ 0.4 A 240 VAC |
| Dissipated power | 15 W | 12 W |
| BUS output voltage | 28 VDC rated (SELV - EN60950-1) | 28 VDC rated (SELV - EN60950-1) |
| Max. current output | 1.6 A (1 A continuous + 0.6 A with cycle 30 s ON - 180 s OFF) | 1 A (0.6 A continuous + 0.4 A with cycle 60 s ON - 120 s OFF) |
| Protection degree | IP30 | IP30 |
| Operating temperature | -5 °C ~ +35 °C (indoor use) | -5 °C ~ +35 °C (indoor use) |
| Dimensions | 140 x 115 x 65 mm (8 modules DIN 60715 TH35) | 108 x 97 x 63 mm (6 modules DIN 60715 TH35) |

Logical system sizing

Due Fili Plus video door entry system with maximum expansion




Logic diagram



Logical system sizing

A system can have a maximum of **32 blocks**; each block can be logically represented as follows:



Consequently, the maximum system capacity is as follows:

Capacity for each block

Indoor stations 200

Capacity for each island

Indoor stations 40

Outdoor stations (electronic units and interfaces 69AM) 14

Switchboards 4

BUS controllable relays (modules 69PH) 16 (8)

Push buttons interfaced on BUS (modules 6120) 16 (8)

Separator 692S.1 16*

* 8 connected in "in-out"

x32

Overall system capacity

Max total cable run of the branch in conversation 2,000 m

Max cable length between the two furthest devices, shunting not included 1,200 m

Main outdoor stations 36

Expansion interfaces 69RS.1 32*

* 8 connected in "in-out"

Cables to use and maximum distances achievable

Recommended cables for any type of **outdoor/indoor** installation.

Use the same type of cable in the same installation. Do not use an Elvox cable with a UTP cable.

Elvox cables for indoor use



732H.E.100 (Eca)
732H.E.500 (Eca)

Elvox cables for outdoor/indoor use (with LSZH sheath)




732I.E.100 (Eca)
732I.E.500 (Eca)



732I.C.100 (Cca)

UTP cables Cat5 and Cat6

Using UTP cables in the system requires the use of certain specific system devices for this type of cable: riser splitter **69DV/5**, concentrator **69MX/5** and amplifier **692M/5**.



Twist the pairs of cables as shown in the figure

Basic rules for system sizing


When designing the system, certain preliminary checks should be carried out to assess the distances and the maximum current required by the devices:

- maximum current with all the devices on standby (no conversation in progress);
- maximum current with one conversation/call in progress;
- video signal level of the indoor station (video entryphone) furthest from the outdoor station (entrance panel);
- power supply voltage level of the indoor station (video entryphone) furthest from the power supply unit.

Please refer to the tables on pages 66 and 67 of the Due Fili Plus devices for: the absorption current, the current outputs from the power supply units, the attenuation/amplification of the video signal and the resistance of the Elvox cables.

Example of checks on a typical system with:

- 6 video entryphones 7559;
- 2 video distributors 692D;
- 1 power supply unit 40110;
- 1 Pixel entrance panel with audio/video electronic unit 41005.



Basic rules for system sizing

Maximum current with all the devices on standby:

| | | | |
|------------------------------------|-----|-------|---|
| Video entryphones 7559: | 6 x | 17 mA | + |
| Video distributors 692D: | 2 x | 0 mA | + |
| Audio/video electronic unit 41005: | 1 x | 40 mA | + |

Maximum absorbed current:

142 mA (less than 1000 mA, current output from the power supply unit 40110)

Maximum current with one conversation/call in progress and electrical lock activation:

| | | | |
|---|-----|--------|---|
| Video entryphone 7559 in operation: | 1 x | 280 mA | + |
| Video entryphones 7559 on standby: | 5 x | 17 mA | + |
| Video distributors 692D: | 2 x | 0 mA | + |
| Audio/video electronic unit 41005 in operation: | 1 x | 250 mA | + |

Maximum absorbed current:

615 mA (less than 1000 mA, current output from the power supply unit 40110)

Video signal level of the indoor station (video entryphone) furthest from the outdoor station (entrance panel):

| | | |
|---|---------|---|
| Video signal level at entrance panel output with audio/video electronic unit 41005: | 16 dBm | - |
| Throughpass attenuation, 1st video distributor 692D: | 0.5 dB | - |
| Video output attenuation, 2nd video distributor 692D: | 20 dB | - |
| Minimum video signal level in video entryphone 7559: | -20 dBm | |

Maximum attenuation on the cable run (TPEA + TAD1 + TD12 + TDPI):

15.5 dB

Maximum distance between furthest indoor station and outdoor station = $15.5 / 5 \times 100 = 310$ m (attenuation of Elvox cable type 732x... of 5 dB every 100 m)

Power supply voltage level of the indoor station (video entryphone) furthest from the power supply unit:

| | | |
|--|--------|---|
| Power supply unit 40110 output voltage: | 28 VDC | - |
| Minimum power supply voltage level of video entryphone 7559: | 24 VDC | |

Maximum attenuation on the cable run (TAD1 + TD12 + TDPI):

4 VDC

The maximum distance between the furthest indoor station and the power supply unit should be assessed while considering the resistance of the cable (3.8 Ω/ 100 m with Elvox cable type 732x...) and the currents absorbed by the indoor stations in the various runs:

TAD1 run: $365 \text{ mA} = 5 \times 17 \text{ mA}$ (Video entryphones 7559 on standby) + 1 x 280 mA (Video entryphones 7559 in operation)
 TD12 run: $297 \text{ mA} = 1 \times 17 \text{ mA}$ (Video entryphones 7559 on standby) + 1 x 280 mA (Video entryphones 7559 in operation)
 TDPI run: 280 mA

Video and audio door entry systems: system characteristics

Summary table of absorptions and video signal level

Audio/video indoor stations, audio indoor stations and reception switchboards

| Code | Description | Min level of video signal (dBm) | Absorption (mA) | | Absorption (mA) |
|----------|--|---------------------------------|-----------------|---------------------|-----------------|
| | | | Rest | Maximum consumption | |
| 7539 | Tab Free 3.5 hands-free video entryphone, white | | 10 | 160 | |
| 7548 | Tab 4.3 video entryphone with handset without intercom., white | | 18 | 180 | |
| 7549 | Tab 4.3 video entryphone with handset, white | | 18 | 180 | |
| 7558 | Tab Free 4.3 hands-free video entryphone, white | | 17 | 280 | |
| 7559 | Tab Free 4.3 hands-free video entryphone, white | | 17 | 280 | |
| 40505 | Tab 7 hands-free video entryphone, white | | 25 | 350 | |
| 40507 | Tab 7S Wi-Fi hands-free video entryphone, white ⁽¹⁾ | | 120 | 400 | |
| 40515 | Tab 5S Up Wi-Fi hands-free video entryphone, white | | 55 | 420 | |
| 40517 | Tab 7S Up Wi-Fi hands-free video entryphone, white | | 58 | 480 | |
| 8879.1 | Surface mounting entryphone, white | | 10 | 160 | |
| 8879.1/D | Surface mounting entryphone, teleloop, white | | 10 | 160 | |
| 7509 | Tab jr. entryphone with handset, white | | 7 | 100 | |
| 7509/D | Tab jr. entryphone with handset, teleloop, white | | 7 | 100 | |
| 6901 | Surface mounting hands-free entryphone, white | | 10 | 110 | |
| 6901/D | Surface mounting hands-free entryphone, teleloop, white | | 10 | 110 | |
| 6209/P | Petrarca entryphone, white | | 10 | 65 | |
| 6209/D | Petrarca entryphone, teleloop, white | | 10 | 65 | |
| 40540 | Voxie entryphone with handset and 2 push buttons, white | | 10 | 100 | |
| 40542 | Voxie entryphone with handset and 6 push buttons, white | | 10 | 100 | |
| 40547 | Voxie hands-free entryphone with 7 push buttons, white | | 10 | 140 | |
| 40510 | 7" reception switchboard, black ⁽¹⁾ | -20 | 86 | 300 | |
| 945F | Reception switchboard, black ⁽¹⁾ | - | 25 | 150 | |

The consumption of devices powered locally, via additional power supply units, should not be calculated at less than 50 mA residual during a call.

1) With additional power supply unit 6923.

Audio/video and audio electronic units

| Code | Description | Video signal level (dBm) | Absorption (mA) | | | Absorption (mA) |
|-----------|--|--------------------------|-----------------|------|--------------------------------|-----------------|
| | | | Rest | Talk | Conversation + electrical lock | |
| 6931 | Audio entrance panel Due Fili unit | | 60 | 265 | 415 | |
| 6932 | Audio entrance panel Due Fili unit | | 60 | 265 | 415 | |
| 41000 | Due Fili Plus basic audio unit | | 25 | 120 | 180 | |
| 40131 | Due Fili Plus audio unit | | 25 | 80 | 140 | |
| 40424 | Due Fili Plus audio entrance panel with keyboard, display and electronic contacts list | | 120 | 280 | 330 | |
| 40425 | Due Fili Plus audio entrance panel with keyboard, display and electronic contacts list | | 120 | 280 | 330 | |
| 13F1 | Due Fili Plus audio unit | | 40 | 250 | 350 | |
| 13F3 | Due Fili Plus audio unit with 8 push buttons | | 60 | 260 | 410 | |
| 13F3.B | Due Fili Plus audio white LED unit with 8 push buttons | | 60 | 260 | 410 | |
| 13F4 | Due Fili Plus audio unit with steel buttons | | 120 | 300 | 450 | |
| 13F4.B | Due Fili Plus audio white LED unit with steel keyboard | | 120 | 300 | 450 | |
| 13A4.B | Due Fili Plus audio white LED unit with steel keyboard | | 120 | 300 | 450 | |
| 13A4.B.43 | Due Fili Plus audio white LED unit with gold keyboard | | 120 | 300 | 450 | |
| 41002 | Due Fili Plus audio teleloop IN video unit | | 40 | 130 | 180 | |
| 41005 | Due Fili Plus audio/video teleloop wide-angle unit | | 40 | 200 | 250 | |
| 40135 | Due Fili Plus audio video unit | | 40 | 200 | 250 | |
| 40404 | Due Fili Plus audio/video entrance panel with keyboard, display and electronic contacts list | | 120 | 280 | 330 | |
| 40405 | Due Fili Plus audio/video entrance panel with keyboard, display and electronic contacts list | | 120 | 280 | 330 | |
| 13F2.1 | Due Fili Plus audio/video unit for cover plate 13K1 | | 40 | 250 | 350 | |
| 13F5 | Due Fili Plus audio/video unit for entrance panel with 8 pushb. | | 60 | 260 | 410 | |
| 13F5.B | Due Fili Plus audio/video white LED unit with 8 push buttons | | 60 | 260 | 410 | |
| 13F7 | Due Fili Plus a/v unit with steel keyboard | | 120 | 300 | 450 | |
| 13F7.B | Due Fili Plus audio/video white LED unit with steel keyboard | | 120 | 300 | 450 | |
| 13A7.B | Due Fili Plus audio/video white LED unit with steel keyboard | | 120 | 300 | 450 | |
| 13A7.B.43 | Due Fili Plus audio/video white LED unit with gold keyboard | | 120 | 300 | 450 | |
| 69AM/T | Selettore video per 4 telecamere | +10 | 25 | 50 | - | |
| 657C | Due Fili colour video unit | | 20 | 180 | - | |

The consumption of devices powered locally, via additional power supply units, should not be calculated at less than 50 mA residual during a call.

Video and audio door entry systems: system characteristics

Summary table of absorptions and video signal level

System components for vertical BUS

| Code | Description | Video signal attenuation/amplification (dB) | Absorption (mA) | | Absorption (mA) |
|----------|---|---|---------------------------------|---|-----------------------|
| | | | Main and secondary vertical BUS | Function | |
| 691D | Single-output passive Video Distributor | -0.5 riser line -20 tap-off line | 0 | 0 | 0 |
| 692D | Passive video distributor on landing | -0.5 riser line -20 tap-off line | 0 | 0 | 0 |
| 692S.1 | Separator for Due Fili Plus systems | -0.2 riser line 0 tap-off line | 15 | 40 (Main BUS) 25 (Secondary BUS) | 50 |
| 69RH | Programmable device with 2 relays | 0 | 15 | 80 | 0 |
| 69RH/L | Programmable device with 2 relays | 0 | 15 | 80 | 0 |
| 69DM | Digibus / Due Fili Plus backbone interface | 0 | 25 | 100 (Main BUS) | 40 (Secondary BUS) |
| 69RS.1 | Expansion interface for 200 indoor stations | -0.2 riser line 0 tap-off line | 15 | 40 (Main BUS) 25 (Secondary BUS) | 50 (48) |
| 692M | Video signal riser amplifier | +6 or +14 | 20 (24) | 50 (48) | 0 |
| 6120 | Interface for 2 Due Fili Plus push buttons | 0 | 2 | 10 | 0 |
| 69MD | Due Fili Plus standard signal interface | 0 | 10 | 60 | 0 |
| 0170/101 | Relay for call repetition | 0 | 0 | 0 | 0 |
| 693T | Interface for camera with CVBS video signal | 0 | 20 | 100 | 0 |
| 692E | Overvoltage protection device | 0 | 0 | 0 | 0 |
| 692G | Earth separator | 0 | 0 | 100 | 0 |

The main vertical BUS is the connection backbone before the separator 692S.1, while the secondary vertical BUS is the one after the separator.

System components for vertical and horizontal BUS

| Code | Description | Video signal attenuation/amplification (dB) | Absorption (mA) | | Absorption (mA) |
|--------|--|---|---------------------------------|----------------|-----------------|
| | | | Main and secondary vertical BUS | Horizontal BUS | |
| 69PH | Programmable device with 2 relays | 0 | 15 | 40 | 15 40 |
| 69DV | Riser splitter in 4 riser lines | -0.2 riser line 0 tap-off line | 15 | 50 | 15 50 |
| 69DV/5 | Riser splitter in 4 Cat5 lines | -0.2 riser line 0 tap-off line | 15 | 50 | 15 50 |
| 69MX | Concentrator for 4 parallel entrance panels | +16 | 25 | 50 | 25 50 |
| 69MX/5 | Concentrator for 4 parallel entrance panels Cat. 5 | +16 | 25 | 50 | 25 50 |
| 01415 | Video entry system gateway Due Fili Plus | 0 | 120 | 300 | 120 300 |

The main vertical BUS is the connection backbone before the separator 692S.1, while the secondary vertical BUS is the one after the separator.



Cables

| Code | Description | Total attenuation (dBm) | Resistor (Ω) |
|------------|--|-------------------------|--------------|
| 732H.E.100 | Due Fili Plus 2x1 cable for internal laying PVC Eca 100 m | -5 | 3.8 |
| 732H.E.500 | Due Fili Plus 2x1 cable for internal laying PVC Eca 500 m | -25 | 19 |
| 732I.C.100 | Due Fili Plus 2x1 cable LSZH Cca 100 m purple | -5 | 3.8 |
| 732I.E.100 | Due Fili Plus 2x1 cable for external laying LSZH Eca 100 m | -5 | 3.8 |
| 732I.E.500 | Due Fili Plus 2x1 cable for external laying LSZH Eca 500 m | -25 | 19 |

Power supply units

| Code | Description | Current supplied (mA) | |
|-------|---|-----------------------|--------------|
| | | Continuous | Intermittent |
| 40100 | Due Fili Plus power supply unit for audio kit | 150 | 510 |

Example of a typical system: villa with 1 video entryphone.



Key
A - Maximum distance between the indoor station and the furthest entrance panels.

B - Maximum distance between the entrance panel and the power supply unit.

| Type of cable | Max distance A | Max distance B |
|------------------------------|----------------|----------------|
| 732H.E., 732I.E., 732I.C.. | 700 m | 200 m |
| Cat.5 or Cat.6 | 570 m | 200 m |
| Twisted phone | 120 m | 40 m |
| Single > 0.2 mm ² | 50 m | |

| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B |
|------------------------------|-------------------------|----------------|----------------|
| 732H.E., 732I.E., 732I.C.. | 2 | 1200 m | 200 m |
| Cat.5 or Cat.6 | 2 | 970 m | 200 m |
| Twisted phone | 0 | 120 m | 40 m |
| Single > 0.2 mm ² | 0 | 50 m | |


Table of configuration of a video door entry system with amplifiers

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C.).

Example of a typical system: villa with 1 Tab 7S Up or Tab 5S Up connected video entryphone.



1300 series entrance panel



Power supply unit



Tab 7S Up video entryphone




The use of video amplifiers 692M does not lengthen the distances.
1) Energy saving mode active or not.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).



* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.



Key
 B - Maximum distance between the entrance panel and the power supply unit.
 C - Maximum distance between the power supply unit and the furthest indoor station.

| Type of cable | Max distance B | Max distance C | |
|----------------------------|----------------|--------------------|--------------------|
| | | Tab 7S Up (40517) | Tab 5S Up (40515) |
| 732H.E., 732I.E., 732I.C.. | 200 m | 230 m ¹ | 300 m ¹ |
| Cat.5 or Cat.6 | 200 m | 210 m ¹ | 270 m ¹ |
| Twisted phone | 40 m | 20 m ¹ | 40 m ¹ |

Example of a typical system: villa with 4 video entryphones.



| Type of cable | Max distance A | Max distance B |
|------------------------------|----------------|----------------|
| 732H.E., 732I.E., 732I.C.. | 320 m | 200 m |
| Cat.5 or Cat.6 | 250 m | 200 m |
| Twisted phone | 100 m | 40 m |
| Single > 0.2 mm ² | 50 m | |

Table relating to the diagram in configuration with 1 entrance panel, 4 individually activated indoor stations, power supply unit and video distributor.



Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C.).

Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.

Example of typical system: villa with 4 video entryphones and extension of the cable runs, via riser amplifier.



Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.

| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B | Max total cable run (of the branch in conversation) |
|----------------------------|-------------------------|----------------|----------------|---|
| 732H.E., 732I.E., 732I.C.. | 1 | 600 m | 200 m | 2000 m |
| 732H.E., 732I.E., 732I.C.. | 2 | 900 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 1 | 510 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 2 | 770 m | 200 m | 2000 m |

Table relating to the diagram in configuration with 1 entrance panel, 4 individually activated indoor stations, power supply unit and video distributor.

Use amplifier 692M for cables 732H.E... 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.



Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

** Position the 692M amplifier at least 200 m from the entrance panel or previous 692M.

Example of a typical system: villa with 4 Tab 7S Up and Tab 5S Up connected video entryphones.



| Type of cable | Max distance A | Max distance B | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------|----------------|----------------|--------------------|--------------------|---|
| | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 280 m | 200 m | 110 m ¹ | 130 m ¹ | 2000 m |
| | | | 70 m ² | 100 m ² | |
| Cat.5 or Cat.6 | 210 m | 200 m | 90 m ¹ | 110 m ¹ | 1500 m |
| | | | 60 m ¹ | 80 m ¹ | |
| Twisted phone | 120 m | 40 m | Not applicable | 30 m ¹ | 1000 m |
| | | | | 20 m ¹ | |

Table relating to the diagram in configuration with 1 entrance panel, 4 indoor stations, power supply unit and video distributor.

- 1) Energy saving mode active.
- 2) Energy saving mode not active.

Notes:


In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).


* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.

Video and audio door entry systems: system characteristics

Example of a typical system: villa with 4 Tab 7S Up and Tab 5S Up connected video entryphones and extension of the cable runs, via riser amplifier.



Video and audio door entry systems: system characteristics



| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B | Max distance C | | Max cable run (of the branch in conversation) |
|------------------------------|-------------------------|----------------|----------------|--------------------|--------------------|---|
| | | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E..., 732I.C.. | 1 | - | 200 m | 110 m ¹ | 130 m ¹ | 2000 m |
| | | | | 70 m ² | 110 m ² | |
| Cat.5 or Cat.6 | 1 | 300 m | 200 m | 90 m ¹ | 130 m ¹ | 1500 m |
| | | | | 60 m ² | 80 m ² | |

Table relating to the diagram in configuration with 1 entrance panel, 4 indoor stations, power supply unit and video distributor. Use amplifier 692M for cables 732H.E..., 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.

- 1) Energy saving mode active.
- 2) Energy saving mode not active.



Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device. The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

- * Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.
- ** Position the 692M amplifier at least 200 m from the entrance panel or previous 692M.

Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.
 C - Maximum distance between the power supply unit and the furthest indoor station.

Example of a typical system: two-family home with 1 video entryphone per home.



| Type of cable | Max distance A | Max distance B | Max cable run (of the branch in conversation) |
|------------------------------|----------------|----------------|---|
| 732H.E., 732I.E., 732I.C. | 600 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 500 m | 200 m | 2000 m |
| Twisted phone | 100 m | 40 m | 2000 m |
| Single > 0.2 mm ² | 50 m | | 100 m |

Table relating to configuration with 1 entrance panel, 1 indoor station per call, power supply unit and riser splitter



Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.

Example of a typical system: two-family home with 1 video entryphone per home and extension of the cable runs, via riser amplifier.



| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B | Max total cable run (of the branch in conversation) |
|----------------------------|-------------------------|----------------|----------------|---|
| 732H.E., 732I.E., 732I.C.. | 1 | 970 m | 200 m | 2000 m |
| 732H.E., 732I.E., 732I.C.. | 2 | 1200 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 1 | 800 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 2 | 1000 m | 200 m | 2000 m |

Table relating to configuration with 1 entrance panel, 1 indoor station per call, power supply unit and riser splitter. Use amplifier 692M for cables 732H.E..., 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.




Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.

Notes:
 In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

** Position the 692M amplifier at least 200 m from the entrance panel or previous 692M.

Example of a typical system: two-family home with 1 Tab 7S Up and Tab 5S Up connected video entryphone per home.



| Type of cable | Max distance B | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------|----------------|----------------------|----------------------|--|
| | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 200 m | 130 m ¹ | 160 m ¹ | 2000 m |
| Cat.5 or Cat.6 | 200 m | 110 m ¹ | 130 m ¹ | 1500 m |
| Twisted phone | 40 m | 20 m ¹ | 30 m ¹ | 1000 m |

Table relating to configuration with 1 entrance panel, 1 indoor station per call, power supply unit and riser splitter.
The use of video amplifiers 692M does not lengthen the distances.

1) Energy saving mode active or not.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.


Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.
C - Maximum distance between the power supply unit and the furthest indoor station.

Video and audio door entry systems: system characteristics

Example of a typical system: apartment building with video door entry system with up to 8 indoor stations.



Video and audio door entry systems: system characteristics



| Type of cable | Max distance A | Max distance B | Max cable run (of the branch in conversation) |
|------------------------------|----------------|----------------|--|
| 732H.E.., 732I.E.., 732I.C.. | 320 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 260 m | 200 m | 2000 m |
| Twisted phone | 100 m | 40 m | 2000 m |
| Single > 0.2 mm ² | 50 m | | 100 m |

Table relating to configuration with 1 entrance panel, 8 individually activated indoor stations, power supply unit and video distributor

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E., 732I.E. and 732I.C.).


Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.

Video and audio door entry systems: system characteristics

Example of a typical system: apartment building with video door entry system with up to 8 indoor stations and extension of the cable runs, via riser amplifier.



Video and audio door entry systems: system characteristics



| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B | Max cable run (of the branch in conversation) |
|----------------------------|-------------------------|----------------|----------------|---|
| 732H.E., 732I.E., 732I.C.. | 1 | 550 m | 200 m | 2000 m |
| 732H.E., 732I.E., 732I.C.. | 2 | 800 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 1 | 450 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 2 | 650 m | 200 m | 2000 m |

Table relating to configuration with 1 entrance panel, 8 individually activated indoor stations, power supply unit and video distributor. Use amplifier 692M for cables 732H.E., 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

In a system with extended cable runs use only the cables indicated in the table.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).


** Position the 692M amplifier at least 200 m from the entrance panel or previous 692M.

Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.

Example of a typical system: apartment building with video door entry system with Tab 7S Up and Tab 5S Up connected video entryphones.



Video and audio door entry systems: system characteristics



| Type of cable | Max distance A | Max distance B | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------|----------------|----------------|----------------------|----------------------|---|
| | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 250 m | 200 m | 50 m ¹ | 70 m ¹ | 2000 m |
| Cat.5 or Cat.6 | 180 m | 200 m | 50 m ¹ | 60 m ¹ | 1500 m |

Table relating to configuration with 1 entrance panel, 8 indoor stations, power supply unit and video distributor.

The use of video amplifiers 692M does not lengthen the distances.

1) Energy saving mode active

Notes: In the event that the use of different video entryphone models is required, check the [entryphone compatibility table](#).

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.



(732H.E, 732I.E and 732I.C).

Key

B - Maximum distance between the entrance panel and the power source

C - Maximum distance between the power supply unit and the furthest indoor station

Example of a typical system: residential complex with video door entry system with up to 200 indoor stations.



| Type of cable | Max distance A | Max distance B | Max cable run (of the branch in conversation) |
|----------------------------|----------------|----------------|---|
| 732H.E., 732I.E., 732I.C.. | 570 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 470 m | 200 m | 2000 m |

Maximum number of riser splitters: 2 devices in series for a maximum of 8 risers, or connect 4 riser splitters in cascade to the outputs of another splitter for a maximum of 16 risers. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

In a system with 200 indoor stations use only the cables indicated in the table.


The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C.).

Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.


Video and audio door entry systems: system characteristics

Example of a typical system: residential complex with video door entry system with up to 200 connected video entryphones; maximum 14 Tab 7S Up or 16 Tab 5S Up per riser.

The installation of a larger quantity of Tab 7S Up or Tab 5S Up per riser is possible, if you divide the connected video entryphones in several islands, using the separator 692S.1.



Video and audio door entry systems: system characteristics



| Type of cable | Max distance A | Max distance B | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------|----------------|----------------|-------------------|-------------------|---|
| | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 570 m | 200 m | 50 m ¹ | 70 m ¹ | 2000 m |
| Cat.5 or Cat.6 | 470 m | 200 m | 50 m ¹ | 60 m ¹ | 1500 m |

Maximum number of riser splitters: 2 devices in series for a maximum of 8 risers, or connect 4 riser splitters in cascade to the outputs of another splitter for a maximum of 16 risers. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser.

1) Energy saving mode active.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.


In a system with 200 indoor stations use only the cables indicated in the table.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.

Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.
C - Maximum distance between the power supply unit and the furthest indoor station.

Example of a typical system: residential complex with video door entry system with reception switchboard and up to 200 indoor stations.



| Type of cable | Max distance A | Max distance B1 | Max distance B2 | Max cable run (of the branch in conversation) |
|----------------------------|----------------|-----------------|-----------------|---|
| 732H.E., 732I.E., 732I.C.. | 840 m | 520 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 710 m | 440 m | 200 m | 2000 m |

Maximum number of riser splitters: 2 devices in series. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

In a system with 200 indoor stations use only the cables indicated in the table.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C.).

Key

A - Maximum distance between the indoor station and the furthest entrance panels.

B - Maximum distance between the entrance panel and the power supply unit.


Video and audio door entry systems: system characteristics

Example of a typical system: residential complex with video door entry system with reception switchboard and up to 200 connected video entryphones; maximum 14 Tab 7S Up or 16 Tab 5S Up per riser.

The installation of a larger quantity of Tab 7S Up or Tab 5S Up per riser is possible, if you divide the connected video entryphones in several islands, using the separator 692S.1.



Video and audio door entry systems: system characteristics



| Type of cable | Max distance A | Max distance B1 | Max distance B2 | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------|----------------|-----------------|-----------------|-------------------|-------------------|---|
| | | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 840 m | 520 m | 200 m | 50 m ¹ | 70 m ¹ | 2000 m |
| Cat.5 or Cat.6 | 710 m | 440 m | 200 m | 50 m ¹ | 60 m ¹ | 1500 m |

Maximum number of riser splitters: 2 devices in series. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser.

1) Energy saving mode active.


Notes:
In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.
In a system with 200 indoor stations use only the cables indicated in the table.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.

Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.
 C - Maximum distance between the power supply unit and the furthest indoor station.

Example of a typical system: residential complex with video door entry system with up to 500 indoor stations.



| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B1 | Max distance B2 | Max cable run (of the branch in conversation) |
|----------------------------|-------------------------|----------------|-----------------|-----------------|---|
| 732H.E., 732I.E., 732I.C.. | 1 | 840 m | 520 m | 200 m | 2000 m |
| Cat.5 or Cat.6 | 1 | 710 m | 440 m | 200 m | 2000 m |

Table relating to configuration with 1 outdoor station and individually activated indoor stations. In the system, you can connect up to a maximum of 32 69RS.1 and maximum 10 connected to one another in in-out. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser. Use amplifier 692M for cables 732H.E..., 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

In a system with 500 indoor stations use only the cables indicated in the table.

The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

** Connect a maximum of 8 in/out 69RS.1 devices in the same electrical panel (max total length of the in/out cable: 7 m).

Key
 A - Maximum distance between the indoor station and the furthest entrance panels.
 B - Maximum distance between the entrance panel and the power supply unit.


Video and audio door entry systems: system characteristics

Example of a typical system: residential complex with video door entry system and up to 500 connected video entryphones; maximum 14 Tab 7S Up or 16 Tab 5S Up per riser.

The installation of a larger quantity of Tab 7S Up or Tab 5S Up per riser is possible, if you divide the connected video entryphones in several islands, using the separator 692S.1.



Video and audio door entry systems: system characteristics



| Type of cable | Video amplifiers (692M) | Max distance A | Max distance B1 | Max distance B2 | Max distance C | | Max cable run (of the branch in conversation) |
|----------------------------------|-------------------------|----------------|-----------------|-----------------|-------------------|-------------------|---|
| | | | | | Tab 7S Up (40517) | Tab 5S Up (40515) | |
| 732H.E., 732I.E., 732I.C.. | 1 | 840 m | 520 m | 200 m | 50 m ¹ | 70 m ¹ | 2000 m |
| Cat.5 or Cat.6 | 1 | 710 m | 440 m | 200 m | 50 m ¹ | 60 m ¹ | 1500 m |

Table relating to configuration with 1 outdoor station and individually activated indoor stations. In the system, you can connect up to a maximum of 32 69RS.1 and maximum 10 connected to one another in in-out. The maximum distance and the extended cable are taken into account for a single riser of the 69DV, from the entrance panel to the last device on the riser. Use amplifier 692M for cables 732H.E..., 732I.E... and 732I.C... or 692M/5 for Cat.5 and Cat.6 cables.

1) Energy saving mode active.

Notes:

In the event that the use of different video entryphone models is required, check the distances of the applicable cable runs. Whatever the conditions, the supply voltage at the video entryphone input must not be less than 24 VDC for each device.

In a system with 500 indoor stations use only the cables indicated in the table.


The maximum distance between the additional power supply unit 6923 and the locally powered devices (entrance panels, video entryphones, switchboards, etc.) is 10 m with Elvox cable (732H.E, 732I.E and 732I.C).

* Depending on the type of system built, assess whether the use of an additional power supply unit 6923 may be necessary.

** Connect a maximum of 8 in/out 69RS.1 devices in the same electrical panel (max total length of the in/out cable: 7 m).


Key
A - Maximum distance between the indoor station and the furthest entrance panels.
B - Maximum distance between the entrance panel and the power supply unit.
C - Maximum distance between the power supply unit and the furthest indoor station.

Cables to use and maximum distances achievable



The maximum length of the cable run in the **branch in conversation**, including all shunting, must be less than 2,000 m (using Elvox or CAT5/6 cables with twisted pair cables).

Power supply




- On standby or during a call/conversation, the sum of the consumption of all the devices powered by a single power supply unit 40110 / 6922.1 must not exceed the maximum value of the current it can dispense. Whatever the conditions, it must be:
$$C_{AL} > C_{PL} + C_{RE}$$

N.B.: the consumption of devices powered locally, via additional power supply units, should not be calculated at less than 50 mA residual during a call.

- Whatever the conditions, the supply voltage must not be less than 24 VDC for each device.

N.B.: for 13Fx and Pixel outdoor stations, using Elvox 732... cable entails that the maximum distance between these and the power supply unit should be 200 metres.


Video signal attenuation



The video signal level that reaches any indoor station must not be less than -20 dBm. For the calculation, take into account the level transmitted by the audio/video unit of the outdoor station, the attenuation of the cable calculated on only the direct run and of the effect of all the devices that may be present along the run (see tables on pages 66 and 67).

In the example above, you must check that:

Therefore, the sum of the cable lengths must be less than 300 metres, using Elvox cables.



692M - Riser amplifier

Should it be necessary to exceed the maximum cable length permitted, video signal amplifiers 692M can be used to regenerate the video signal, with a gain of +6 or +14 dB programmable.


A maximum of 2 video amplifiers 692M can be inserted on a single video run between an Outdoor Station and an Indoor Station.

The gain of each amplifier must be set in relation to the input level so that the output does not exceed the nominal rating of +16 dBm.


Max level of input signal for amplification 6 dB = **+9 dBm**
Max level of input signal for amplification 14 dB = **+1 dBm**

Video signal attenuation

Using Elvox cable and 2 692M with amplification +6 dB, the maximum theoretical length of the run is 960 m.




Using Elvox cable and 2 692M with amplification +14 dB, the maximum theoretical length of the run is 1,280 m.




Video signal attenuation

The 1st first indoor station and the intermediate ones in an in-out connection should not be terminated, only the last indoor station in the sequence should be terminated on position 100 Ω if Elvox cables are being used or on position 50 Ω if CAT5/6 twisted pair cables are being used.




Example of video indoor station termination with dip switch



Both Dip switches OFF:
Pass-through connection




One Dip switch ON:
Termination 100 Ω for Elvox cables (type 732x...)



Both Dip switches ON:
Termination 50 Ω for CAT5/6 twisted pair cables.




Video signal attenuation



691D - Video signal floor distributor


691D is a passive distributor that allows connection to the riser of 1 single shunting for video indoor stations and is capable of allowing a maximum of 700 mA to pass for the power supply - typically - of 2 video indoor stations in parallel with simultaneous switch-on. The shunting must have a length of less than 30 m.



692D - Video signal floor distributor



692D is a passive distributor that allows connection to the riser of 4 shunts for video indoor stations and is capable of allowing, for each one, a maximum of 700 mA to pass for the power supply - typically - of 2 video indoor stations in parallel with simultaneous switch-on. The shunting must have a length of less than 30 m.

At least one shunting must under all circumstances be connected to output 1A-1B. For all other outputs: if used, the corresponding jumper must be removed; if not used, you need to leave it in place.




If the riser continues, remove jumper TOUT. Otherwise, move jumper TOUT to position 100 if Elvox cables are being used otherwise to position 50 if CAT5/6 twisted pair cables are being used.

The maximum number of indoor stations that can be connected to the output of each distributor shunting is 5, considering the maximum output current of 691D and 692D. Only the last indoor station of the sequence must be terminated. The limit of the maximum current can be compensated by indoor stations which can be powered locally.



Single-riser systems with single outdoor station



General requirements:

On standby, during a call or a conversation, the sum of the consumption of all the devices powered by a single power supply unit 6922.1 must not exceed the maximum value of the current it can dispense.

Whatever the conditions, the supply voltage must not be less than 24 VDC for each device.

The video signal level that reaches any indoor station must not be less than -20 dBm.

For any connection envisaged, the maximum length of the cable run must be less than 2,000 m (using Elvox or CAT5/6 twisted pair cables) and the number of all devices connected along the cable run must not exceed 50.

All the cable runs concerned by a conversation must be considered (including any separators / closed interfaces) including shunting and converging branches.



Maximum cable lengths (using Elvox cables)

Max Cable Length (Elvox 732H/I) between the two furthest devices, 720 m; extendible up to approximately 1,280 m depending on the type of system and with the use of maximum 2 amplifiers 692M (with programmed gain of +14 dB).

For 13Fx and Pixel outdoor stations, using an Elvox 732H/I cable, the maximum distance between these and the power supply unit is 200 metres.

In the presence of runs without shunting, with in-out connections, the maximum number of indoor stations that can be connected, with one or more in simultaneous switch-on, is 5. Any indoor stations exceeding the consumption limit of 700 mA should be powered locally.



Multi-riser systems with single outdoor station




Riser splitters can be used to obtain up to 8 shunts with 2 69DC connected "in series" (the OUT of the first one connected to the IN of the second, with the minimum possible cable length between the two devices) or up to 16 shunts with 5 69DV connected "in cascade" (OUT1, OUT2, OUT3, OUT4 of the first are connected to the Ins of the others).

In any configuration possible, outputs OUT1, OUT2, OUT3, OUT4 that are not used do not need to be terminated.


Systems with several outdoor stations



The concentrators can be used to connect up to 16 outdoor stations or video sources with 5 69MX connected "in cascade" (the OUT1 of four concentrators are connected to IN1, IN2, IN3, IN4 of the first one). In any configuration possible, inputs IN1, IN2 and outputs OUT1, OUT2, OUT3, OUT4 that are unused do not need to be terminated.




If they need audio outdoor stations, they must under all circumstances be connected to the inputs of the 69MX; for each input a maximum of 3 audio outdoor stations can be connected in parallel.



If the input level is too high (i.e. above +10 dBm), it needs to be attenuated using, for instance, the shunted output of a 692D (attenuation of -20 dB).

Systems with multiple risers and multiple outdoor stations




General Requirements:

On standby, during a call or a conversation, the sum of the consumption of all the devices powered by a single power supply unit 6922.1 must not exceed the maximum value of the current it can dispense.

Whatever the conditions, the supply voltage must not be less than 24 VDC for each device.

The video signal level that reaches any Indoor Station must not be less than -20 dBm.


For any connection envisaged, the maximum length of the cable run in the branch in conversation connecting the two furthest devices must be less than 2,000 m (using Elvox or CAT5/6 cables with twisted pair cables).



For this maximum extension too, all the requirements listed for a single-riser system with single outdoor station must be met (both the "General requirements" indicated as well as those concerning the maximum cable lengths).

If one or more of these cannot be met, you need to create multiple "islands" with the use of separators 692S.1 or multiple "blocks" with the use of interfaces 69RS.1, as illustrated below.

Systems with separators



692S.1 - Separator


Separators 692S.1 are used to create separate communication **Islands** (intercom only between Indoor stations of the same island). In the same **Block** you can connect up to a maximum of 16 separators which should unequivocally be routed via jumpers 0-3.

Besides the case of non-fulfilment of the general requirements or of those about the maximum cable lengths, the separators are used to create:


- systems with multiple risers;
- systems comprising one or more buildings with one or more secondary entrance panels, connected to one or more main entrance panels;
- systems with the presence of "landing" outdoor stations;
- systems with entryphones / video entryphones that do not need to engage the communal riser for intercom conversations.

"A" **No termination:** BUS P enters and exits the device.
"B" **100 Ω termination:** BUS P does not exit the device and Elvox cables are used.
"C" **50 Ω termination:** BUS P does not exit the device and CAT5/6 twisted pair cables are used.

Example 1a - Separators 692S.1 connected in "in-out".




For each island in the system, both the **general requirements** as well as those on the maximum cable lengths must be met. For all the devices, the rules about the **maximum capacity per single block** also apply.




A maximum of eight separators can be connected in in-out. The devices must be connected to one another with the minimum possible cable length. So we recommend their installation in the same electrical panel.

Systems with separators

Example 1b - Separators 692S.1 connected in "in-out".




For each island in the system, both the **general requirements** as well as those on the maximum cable lengths must be met. For all the devices, the rules about the **maximum capacity per single block** also apply.



One special case is the need to split the riser due to a higher number of indoor stations than that permitted: for each island the maximum number of indoor stations that can be connected is 40.

Systems with separators

Example 2 - Separators 692S.1 connected "star point" via riser splitters 69DV.




For each island in the system, both the **general requirements** as well as those on the maximum cable lengths must be met. Only communications (intercom) between indoor stations of the same island are possible. For all the devices, the rules about the **maximum capacity per single block** previously illustrated and specified here also apply.

Capacity for vertical system

| | |
|--|---------|
| Max total cable run of the branch in conversation | 2,000 m |
| Max cable length between the two furthest devices, shunting not included | 1,200 m |
| Outdoor stations | 15 |
| Indoor stations | 200 |
| Switchboards | 4 |
| For a vertical system, the system considered has no expansion interfaces 69RS.1. | |

Systems with separators

Example 3 - Separators 692S.1 connected "star point" via riser splitters 69DV.




For each island in the system, both the **general requirements** as well as those on the maximum cable lengths must be met. Only communications (intercom) between indoor stations of the same island are possible. For all the devices, the rules about the **maximum capacity per single block** previously illustrated and specified here also apply.

Capacity for vertical system

| | |
|--|---------|
| Max total cable run of the branch in conversation | 2,000 m |
| Max cable length between the two furthest devices, shunting not included | 1,200 m |
| Outdoor stations | 15 |
| Indoor stations | 200 |
| Switchboards | 4 |
| For a vertical system, the system considered has no expansion interfaces 69RS.1. | |


Systems with expansion interfaces

If the maximum capacity per single block is still not sufficient, you can use expansion interfaces 69RS.1 to achieve the maximum system capacity.



Expansion interface art. 69RS.1 is a device used in "Due Fili Plus" systems for the connection of the "HORIZONTAL BUS" with the "VERTICAL BUSES": essentially, it performs the transcoding between the "Absolute Addresses" of the system and the "Relative Addresses" of each block.

System with maximum expansion



$$\text{Address} = \text{Rest} [(\text{Absolute Address} - 1) / 200] + 1 \quad \text{Block} = \text{Quotient} [(\text{Absolute Address} - 1) / 200] + 1$$

Example: the absolute address 3741 corresponds to the block address 141 of block 19.

$$\text{Address} = \text{Rest} [(3741 - 1) / 200] + 1 = \text{Rest} [18,7] + 1 = 140 + 1 = 141$$

$$0,7 \times 200$$

$$\text{Block} = \text{Quotient} [(3741 - 1) / 200] + 1 = \text{Quotient} [18,7] + 1 = 18 + 1 = 19$$

Video and audio door entry systems: system characteristics

Systems with expansion interfaces

The following table highlights the ID identifications for the devices connected to the HORIZONTAL BUS according to the ID of the reference router.

| ID 69RS.1 | ID Electronic units | ID Indoor stations | ID Relay modules | ID Push button module | ID Switchboards | ID Separators |
|-----------|---------------------|--------------------|------------------|-----------------------|-----------------|---------------|
| 1 | 8,248 ... 8,235 | 1 ... 200 | 1 ... 8 | 1 ... 8 | 1 ... 4 | 1 ... 16 |
| 2 | 8,234 ... 8,221 | 201 ... 400 | 9 ... 16 | 9 ... 16 | 5 ... 8 | 17 ... 32 |
| 3 | 8,220 ... 8,207 | 401 ... 600 | 17 ... 24 | 17 ... 24 | 9 ... 12 | 33 ... 48 |
| 4 | 8,206 ... 8,193 | 601 ... 800 | 25 ... 32 | 25 ... 32 | 13 ... 16 | 49 ... 64 |
| 5 | 8,192 ... 8,179 | 801 ... 1,000 | 33 ... 40 | 33 ... 40 | 17 ... 20 | 65 ... 80 |
| 6 | 8,178 ... 8,165 | 1,001 ... 1,200 | 41 ... 48 | 41 ... 48 | 21 ... 24 | 81 ... 96 |
| 7 | 8,164 ... 8,151 | 1,201 ... 1,400 | 49 ... 56 | 49 ... 56 | 25 ... 28 | 97 ... 112 |
| 8 | 8,150 ... 8,137 | 1,401 ... 1,600 | 57 ... 64 | 57 ... 64 | 29 ... 32 | 113 ... 128 |
| 9 | 8,136 ... 8,123 | 1,601 ... 1,800 | 65 ... 72 | 65 ... 72 | 33 ... 36 | 129 ... 144 |
| 10 | 8,122 ... 8,109 | 1,801 ... 2,000 | 73 ... 80 | 73 ... 80 | 37 ... 40 | 145 ... 160 |
| 11 | 8,108 ... 8,095 | 2,001 ... 2,200 | 81 ... 88 | 81 ... 88 | 41 ... 44 | 161 ... 176 |
| 12 | 8,094 ... 8,081 | 2,201 ... 2,400 | 89 ... 96 | 89 ... 96 | 45 ... 48 | 177 ... 192 |
| 13 | 8,080 ... 8,067 | 2,401 ... 2,600 | 97 ... 104 | 97 ... 104 | 49 ... 52 | 193 ... 208 |
| 14 | 8,066 ... 8,053 | 2,601 ... 2,800 | 105 ... 112 | 105 ... 112 | 53 ... 56 | 209 ... 224 |
| 15 | 8,052 ... 8,039 | 2,801 ... 3,000 | 113 ... 120 | 113 ... 120 | 57 ... 60 | 225 ... 240 |
| 16 | 8,038 ... 8,025 | 3,001 ... 3,200 | 121 ... 128 | 121 ... 128 | 61 ... 64 | 241 ... 256 |
| 17 | 8,024 ... 8,011 | 3,201 ... 3,400 | 129 ... 136 | 129 ... 136 | 65 ... 68 | 257 ... 272 |
| 18 | 8,010 ... 7,997 | 3,401 ... 3,600 | 137 ... 144 | 137 ... 144 | 69 ... 72 | 273 ... 288 |
| 19 | 7,996 ... 7,983 | 3,601 ... 3,800 | 145 ... 152 | 145 ... 152 | 73 ... 76 | 289 ... 304 |
| 20 | 7,982 ... 7,969 | 3,801 ... 4,000 | 153 ... 160 | 153 ... 160 | 77 ... 80 | 305 ... 320 |
| 21 | 7,968 ... 7,955 | 4,001 ... 4,200 | 161 ... 168 | 161 ... 168 | 81 ... 84 | 321 ... 336 |
| 22 | 7,954 ... 7,941 | 4,201 ... 4,400 | 169 ... 176 | 169 ... 176 | 85 ... 88 | 337 ... 352 |
| 23 | 7,940 ... 7,927 | 4,401 ... 4,600 | 177 ... 184 | 177 ... 184 | 89 ... 92 | 353 ... 368 |
| 24 | 7,926 ... 7,913 | 4,601 ... 4,800 | 185 ... 192 | 185 ... 192 | 93 ... 96 | 369 ... 384 |
| 25 | 7,912 ... 7,899 | 4,801 ... 5,000 | 193 ... 200 | 193 ... 200 | 97 ... 100 | 385 ... 400 |
| 26 | 7,898 ... 7,885 | 5,001 ... 5,200 | 201 ... 208 | 201 ... 208 | 101 ... 104 | 401 ... 416 |
| 27 | 7,884 ... 7,871 | 5,201 ... 5,400 | 209 ... 216 | 209 ... 216 | 105 ... 108 | 417 ... 432 |
| 28 | 7,870 ... 7,857 | 5,401 ... 5,600 | 217 ... 224 | 217 ... 224 | 109 ... 112 | 433 ... 448 |
| 29 | 7,856 ... 7,843 | 5,601 ... 5,800 | 225 ... 232 | 225 ... 232 | 113 ... 116 | 449 ... 464 |
| 30 | 7,842 ... 7,829 | 5,801 ... 6,000 | 233 ... 240 | 233 ... 240 | 117 ... 120 | 465 ... 480 |
| 31 | 7,828 ... 7,815 | 6,001 ... 6,200 | 241 ... 248 | 241 ... 248 | 121 ... 124 | 481 ... 496 |
| 32 | 7,814 ... 7,801 | 6,201 ... 6,400 | 249 ... 256 | 249 ... 256 | 125 ... 128 | 497 ... 512 |


ID attributable to the devices present on the HORIZONTAL BUS.

| ID 69RS.1 | ID Electronic units | ID Indoor stations | ID Relay modules | ID Push button module | ID Switchboards 40510 | ID Separators |
|-----------|---------------------|--------------------|------------------|-----------------------|-----------------------|---------------|
| - | 1 ... 36 | - | 2,951 ... 3,000 | - | 129 ... 144 | - |

In the interface, you can also use **SaveProg** to reallocate the address both to **main outdoor stations** as well as to **relay modules** so that they can receive controls from indoor stations belonging to a block (even in the absence of a conversation). The outdoor stations, to which the address has been reallocated, must be subtracted from the maximum number of outdoor stations per block (14). The relays, to which the address has been reallocated, will be controlled in parallel with the relays of the block with the same address.

Video and audio door entry systems: system characteristics

Systems with expansion interfaces



Other system components

40510 - Reception switchboard




A switchboard 40510 can perform the following functions:

- make and receive audio calls with the indoor stations;
- receive audio or audio/video calls from the outdoor stations;
- perform self-starts on the outdoor stations;
- forward the calls of the outdoor stations to the indoor stations;
- call another switchboard;
- manage (alert) warnings from the indoor stations;
- manage the locks of the outdoor stations, the stair lights and the system relays;
- activate the CCTV cameras for monitoring;
- record call data, warnings and actuations.

In an extended system, a maximum of 128 switchboards can be installed in total (32 risers x 4 switchboards).

A maximum of 4 switchboards can be installed in a block.

A maximum of 16 switchboards can be connected to the horizontal bus in addition to those of the risers.



Other system components


69RH - Relay module



Relay module 69RH is equipped with two relays with normally open contacts, which can operate in two programmable modes:

- 1 - **Relay mode** - auxiliary services (default): the normally open contacts of both are independent and can be timed from 1 to 30 seconds, adjusting the two trimmers located on the printed circuit.
- 2 - **Repeater mode** - call repeater: the normally open contacts of both are independent and can be connected to a ringtone 860A or a mechanical ringtone. You can repeat the call from an outdoor station or indoor station/switchboard (addressed to one or more entryphone or video entryphone groups up to a maximum of 4 groups), operating two different ringtones.

Each 69RH should be allocated an address using jumpers ID0-ID1-ID2.



Other system components


69PH - Relay module



Relay module 69PH is a programmable device equipped with two relays with change-over relay and can be installed on both the Vertical BUS as well as on the Horizontal BUS. If it is installed on the Vertical BUS, it can also be programmed manually with the same modes as relay module 69RH; if on the other hand it is installed on the Horizontal BUS, it can only be programmed using the SaveProg software.

It can operate in the following modes:

- one-position stable relay activated by the indoor stations (default);
- one-position stable relay activated by a call (repeater);
- one-position stable relay activated by buttons F1, F2, lock of the indoor stations;
- one-position stable relay activated by attempted call;
- one-position stable relay activated by attempted group call;
- two-position stable relay activated by the indoor stations;
- two-position stable relay activated by a call;
- call repeater (Standard);
- general call repeater;
- call repeater from 6120;
- roller shutter mode;
- Call in progress.




Other system components

693T - Expansion module for 6931 (with PAL output)



The camera interface module 693T allows you to use cameras with a PAL output as video sources or it can be used as a separate video jointly with dedicated audio electronic units.




Other system components

69AM/T - Video selector for 4 cameras



The video selector for 4 cameras 69AM/T allows the connection to the Due Fili Plus system of 4 cameras with CVBS output. Camera selection is cyclical by way of the lock release button or a dedicated push button after the self-start phase. The selector can also be connected to two auxiliary functions F1 and F2.




+ EXT: Connection for power supply from 6923, the - must be connected to terminal M.
F2: Open collector output, max 100 mA/+12 VDC.
F1: Open collector output, max 100 mA/+12 VDC.
+12V: Load power supply on F1 and/or F2.
GND: Reference ground of +I, 12, +E.
+ I: Active positive output max. 100 mA (+12 VDC when a camera is on).
B1-B2: Due Fili Plus system BUS.

Other system components

6120 - The interface for 2 push buttons



The Interface for 2 push buttons 6120 allows you to use normal push buttons (normally open) to control, via the (vertical) BUS of the Due Fili Plus system, the activation: of the lock on an outdoor station or the landing call of an indoor station or of a relay 69RH/69PH or of functions F1, F2 towards specific entrance panels.




B1-B2: Pair of terminals for BUS line.
IN1: Pair of terminals for the connection of the 1st push button.
IN2: Pair of terminals for the connection of the 2nd push button.
1 2 3: Dip switch for routing the device.
D3: Programming state signalling LED.
ABC: Jumpers for BUS termination.
→: Push button for programming (association of the function of the push buttons).
"A" **No termination:** BUS P enters and exits the device.
"B" **100 Ω termination:** BUS P does not exit the device and Elvox cables are used.
"C" **50 Ω termination:** BUS P does not exit the device and CAT5/6 twisted pair cables are used.


Video and audio door entry systems: multi-row diagrams

Audio/video and audio unit connection for the 1300, Steely and Patavium series with push button call

Audio/video unit: 13F5, 13F5/B




Audio unit: 13F3, 13F3.B




Video and audio door entry systems: multi-row diagrams

Audio/video and audio unit connection for the Pixel, Pixel Heavy and Pixel Up series

Audio/video unit: 41005 and Pixel Up




Audio unit: 41000 and Pixel Up




Audio/video and audio unit connection for the 1300, Steely and Patavium series numerical call


Audio/video unit: 13F7, 13F7/B, 13A7.B, 13A7.B.43




Audio unit: 13F4, 13F4.B, 13A4.B, 13A4.B.43



Audio unit with camera input: 41002 and Pixel Up




System with audio riser and variant with audio switchboard





Note: In audio only systems, the video terminations of all the devices will be left open.

Audio system with 3 outdoor stations for the same riser



Note: In audio only systems, the video terminations of all the devices will be left open.




Note: In audio only systems, the video terminations of all the devices will be left open.

Note: In audio only systems, the video terminations of all the devices will be left open.

Video and audio door entry systems: multi-row diagrams


System with audio/video riser with distributors 692D and audio/video switchboard variant



* Landing call push button

Video and audio door entry systems: multi-row diagrams


System with audio/video riser with distributors 691D and riser splitter 69DV




* Landing call push button

To the power supply unit 40110 / 6922.1

System with audio/video riser without distributors (in-out connection)



Video system with several outdoor stations for the same riser



B.CC23015 EN 222
80073521725621

Energia Positiva. Insieme



Viale Vicenza, 14 36063 Marostica VI - Italy Tel. +39 0424 488 600 Fax +39 0424 488 709 www.vimar.com